Decoupled Power Angle and Voltage Regulation Modes for Electric Springs

Abstract

In this paper, a control method called radial-orbital decomposition (ROD) control is proposed for controlling the voltage of electric springs (ES). The proposed control method decomposed the ES voltage into two components. The radial component can be used in grid voltage regulation in the future smart grid while the orbital component can be used to improve the power factor of the non-critical load that is connected in series with the ES. As a result, the grid voltage regulation and the power factor improvement can be done independently and simultaneously. A two-kilowatts laboratory-scale experiment was done to verify the proposed control method.

I. INTRODUCTION

The energy crisis is one of the major concerns in the human society due to the running out of available energy resources in coming decades [1]. In addition, the exhaustive use of carbon-based fossil fuels, such as coal, natural gas, and petroleum, for the generation of electricity causes the global warming and climate change [2]. Furthermore, the society doubts the reliability and the safety of nuclear energy after the Fukushima Daiichi nuclear disaster in Japan in 2011 [3]. Thereby, the governments worldwide impose policies on urging the power companies to use renewable energy sources [4]–[6] such as, wind, solar, geothermal and ocean wave energy for the replacement. The expanded penetration of using renewable energies for power generation leads to a new revolution in the power grid system in the future.

Traditionally, the power companies manage and control the electricity power generation. The power always flows from generation sides to demand sides. In the future smart power grid arrangement, the adoption of the renewable energy sources for power generation causes two uncertainties. First, the renewable energy sources are decentralized and distributed all over the electricity network. Hence, the power companies lost the controllability on those energy sources. Second, the amount of energy of those intermittence renewable energy sources, such as wind and solar, is unpredictable. Those two issues can cause the power unbalance between the power generation and consumption, which can lead to the instability problem.

Based on the above mentioned problems, one of the possible solutions is to use the demand side management in which the power consumption of loads can adaptively follow the power generation profile. The ways of implementation of such approach are briefly summarized as follow: 1) scheduling of delay-tolerant power demand tasks [7]–[9], 2) real-time pricing [10]–[12], 3) use of energy storage to alleviate peak demands [13] and 4) direct load control or on-off control of smart loads [14]–[16]. Some drawbacks and imperfections are found in those approaches. Methods 1) and 2) are used for reducing the predicted peak load demand but it cannot be used for balancing the power generation and consumption in real time. Method 3) is an effective way but it is an expensive option. Method 4) can adjust the loads to follow power consumption but it requires information communication technologies.

Recently, a new technology, called electric springs (ES), has been introduced, which is a power electronic device integrated into non-critical loads (such as thermal heaters) to form a smart load [17]. The smart load can either generate or absorb reactive powers in order to solving the grid voltage instability problem due to the frustration of intermittence renewable energies. The load shedding is inherently existed feature in the smart load such that the demand side management approach is adopted. The electronic springs can also be embedded with battery storages in such a way that both active and reactive power can either generate or absorb, where the power electronic device used is called the series-connected active-reactive- power-compensation electric springs (PQ-ES) [18]. Research activities are still being done in order to explore the possible functionalities and optimum control methods. However, there is a optimization problem on finding a suitable method for controlling the active and reactive power flows cooperatively on the smart load implemented by the PQ-ES.

In this paper, a new control methodology, called the radial-orbital decomposition (ROD) control method, is proposed. The power amplitude and power angle of the ES-controlled smart load can be controlled independently by adopting this ROD control method. This proposed ROD methodology can be used to control the electrical parameters, such as smart load power factor, smart load apparent power, grid voltage, etc.

A two-kilowatts laboratory-scale experiment was done to verified the proposed control method. The experiment used an PQ-ES connected to an resistive-inductive non-critical load to form a smart load. It is validated that the power factor of the smart load can be improved by using the orbital-controlled ES while the grid voltage regulation can be conducted by using the radial-controlled ES. Both radial and orbital control scheme can be performed simultaneously and independently in one ES.

II. DECOMPOSITION OF ES VOLTAGE

Figure 1 shows an illustrative electrical system diagram in which a power source with a voltage $|V_g|\angle\theta_g$, which represents a supply side voltage source is transferring power $|S_g|\angle\phi_g = P_g + jQ_g$ to the load side through a transmission line with an impedance $|Z_t|\angle\phi_t = R_t + jX_t$. The load side, which has a power $|S_s|\angle\phi_s = P_s + jQ_s$, contains a combination of impedance loads $|Z_i|\angle\phi_i$ and electric springs (ES). Hence, $|S_s|\angle\phi_s$ can be adaptively changed according to the variation of $|V_g|$ with a proper control of the ES voltages. In the above description and our later analysis, all phasor angles denoted as θ and φ are referenced to the grid voltage phasor $|V_s|\angle 0$. All phasor angles denoted by ϕ are power angles representing the displacement angle between the described voltage and current phasors.

The operating principle of the electric string is that if the magnitude of the supply side voltage $|V_g|$ drops (rises), the adjustment of the ES voltage causes the load side power consumption and/or the voltage drop of the transmission line $|V_t|$ reduced (rose) in a way to keep the magnitude of the grid voltage $|V_s|$ unchanged [17].

Figure 2 indicates one of the possible electric spring configurations where the electric spring and a non-critical load $|Z_1|\angle\phi_1$ are connected in series, formulating a smart load. The voltage of the ES, namely $|V_{es}|\angle\theta_{es}$, can be controlled through a feedback system. This is defined as a “series-connected voltage-controlled electric spring”. Another load tied to the grid directly is defined as critical load $|Z_2|\angle\phi_2$, in which the power consumed by this load cannot be controlled by the electric spring. The smart load and the critical load has a power $|S_{s1}|\angle\phi_{s1}$ and $|S_{s2}|\angle\phi_{s2}$ respectively. The relationship between the load side voltage (the grid voltage), the electric spring voltage and the non-critical load voltage is

Fig. 1. Illustrative electrical system with electric springs installed.

Fig. 2. A series-connected voltage-controlled ES with a series-connected constant impedance non-critical load and a critical load that is in parallel with both the ES and the non-critical load.

$$|V_s|\angle\theta_s = |V_{es}|\angle\theta_{es} + |V_o|\angle\theta_o. \quad (1)$$

We assumed that the non-critical load ($|Z_1|\angle\phi_1$) is connected to the electric spring in series to formulate a smart load as shown in Fig. 2. The magnitude of the non-critical load voltage $|V_o|$ can be larger or smaller than that of the grid voltage $|V_s|$. Also, the voltage phasor $|V_o|\angle\theta_o$ can either lead or lag the voltage phasor $|V_s|\angle\theta_s$. Two possible arbitrary phasor diagrams representing Eq. (1) are shown in Fig. 3(a) and Fig. 3(b). In our analysis on this section, we assumed the root mean square value of the grid voltage ($|V_s|$) is unchanged and is equal to $|V_{s_Ref}|$. In order to analyze the operating principle of the electric spring, we decompose $|V_{es}|\angle\theta_{es}$ into two components such that

$$|V_{es}|\angle\theta_{es} = |V_{eso}|\angle\theta_{eso} + |V_{esr}|\angle\theta_{esr} \quad (2)$$

where $|V_{eso}|$ and $|V_{esr}|$ are the magnitude of the two decomposed ES voltage components namely the orbital component and the radial component, respectively. Consequently, θ_{eso} and θ_{esr} are respectively the displacement angles of the two decomposed components, with reference to $|V_s|\angle\theta_s$.

In this decomposition arrangement, the radial component $|V_{esr}|\angle\theta_{esr}$ is either in phase (as shown in Fig. 3(a)) or anti-phase (as shown in Fig. 3(b)) with the non-critical load voltage $|V_o|\angle\theta_o$ such that the equations for $|V_{esr}|\angle\theta_{esr}$ are

Fig. 3. An arbitrary state of the phasor voltages of Eq. (1). The ES voltage is decomposed into two components.

$$\theta_{esr} = \begin{cases} \theta_o & \text{for } |V_o| < |V_s| \\ 0 & \text{for } |V_o| = |V_s| \text{ (No radial-ES)} \\ \theta_o - \pi & \text{for } |V_o| > |V_s| \end{cases} \quad (3)$$

$$|V_{esr}| = ||V_o| - |V_s|| \quad (4)$$

Therefore, the magnitude of the radial-ES voltage is generated in accordance with the magnitude of the non-critical load voltage $|V_o|$ and that of grid voltage $|V_g|$ while the phasor angle of that is locked to follow phasor angle of the non-critical load voltage θ_o .

Considering the orbital component, as shown in Fig. 3(a), the voltage phasor $|V_o|\angle\theta_o$ is leading the reference voltage phasor $|V_s|\angle 0$ while the voltage phasor $|V_{eso}|\angle\theta_{eso}$ is lagging the reference voltage phasor $|V_s|\angle 0$. On the other hand, as shown in Fig. 3(b), the voltage phasor $|V_o|\angle\theta_o$ is lagging while the voltage phasor $|V_{eso}|\angle\theta_{eso}$ is leading the reference voltage phasor $|V_s|\angle 0$. Hence, the polarity of the phasor angle θ_{eso} and θ_o are

$$\begin{aligned} \theta_o > 0 \text{ and } \theta_{eso} < 0 & \text{ for } |V_o|\angle\theta_o \text{ leads } |V_s|\angle 0 \\ \theta_o = \theta_{eso} = 0 & \text{ for } |V_o|\angle\theta_o = |V_s|\angle 0 \text{ (no orbital-ES).} \\ \theta_o < 0 \text{ and } \theta_{eso} > 0 & \text{ for } |V_o|\angle\theta_o \text{ lags } |V_s|\angle 0 \end{aligned} \quad (5)$$

The absolute value of the angle θ_{eso} can be evaluated by considering the sum of the inner angles of the isosceles triangle OAB indicated in Fig. 3(a) or Fig. 3(b).

$$\pi = \angle OAB + \angle OBA + \angle AOB. \quad (6)$$

This can be represented by the absolute value of the phasor angle θ_{eso} and θ_o

$$\pi = |\theta_{eso}| + |\theta_{eso}| + |\theta_o| \quad (7)$$

which gives

$$|\theta_{eso}| = \frac{\pi - |\theta_o|}{2}. \quad (8)$$

Combining Eq. (5) and (8), we have

$$\theta_{eso} = \begin{cases} \frac{\theta_o - \pi}{2} & \text{for } |V_o| \angle \theta_o \text{ leads } |V_s| \angle 0 \\ 0 & \text{for } |V_o| \angle \theta_o = |V_s| \angle 0 \text{ (no orbital-ES)} \\ \frac{\theta_o + \pi}{2} & \text{for } |V_o| \angle \theta_o \text{ lags } |V_s| \angle 0 \end{cases} \quad (9)$$

The $|V_{eso}|$ can be evaluated by using the cosine rule on the triangle OAB as

$$|V_{eso}|^2 = |V_s|^2 + |V_s|^2 + 2|V_s||V_s| \cos \theta_o. \quad (10)$$

Simplifying Eq. (9) and (10), two functions, $f_{\theta\text{-orbital}}(\theta_o)$ and $f_{V\text{-orbital}}(\theta_o)$, can be derived, which are used to control the voltage magnitude and phasor angle of the orbital ES voltage, respectively. We have

$$\begin{cases} \theta_{eso} = f_{\theta\text{-orbital}}(\theta_o) = -\text{sgn}(\theta_o) \cdot \frac{\pi - |\theta_o|}{2} \\ V_{eso} = f_{V\text{-orbital}}(\theta_o) = \sqrt{2|V_s|^2(1 - \cos \theta_o)} \end{cases} \quad \text{for } -\pi < \theta_o < \pi \quad (11)$$

where $\text{sgn}(\cdot)$ is defined as the sign function. Therefore, the orbital-ES voltage phasor is generated in accordance with the phasor angle of the non-critical load voltage θ_o referring to the reference voltage phasor $|V_s| \angle 0$.

III. EFFECT OF THE PROPOSED DECOMPOSITION METHOD

In grid voltage regulation application, the smart load complex power can be adjusted adaptively by applying a suitable ES voltage. It is important to study how the ROD control method affects the variation of the complex power of the smart load. The complex power of the smart load $|S_{s1}| \angle \phi_{s1}$ can be represented by its apparent power $|S_{s1}|$ and its power angle ϕ_{s1} . The apparent power of the smart load, which is the magnitude of the vector sum of real and reactive power, is also the product of its magnitude of the voltage and current, which gives:

$$|S_{s1}| = |V_s| |I_1| \quad (12)$$

According to Fig. 3(a), the power angle of the smart load can be found by

$$\phi_{s1} = \phi_1 - |\theta_o| \quad \text{for } |V_o| \angle \theta_o \text{ leads } |V_s| \angle 0 \quad (13)$$

According to Fig. 3(b), the power angle of the smart load is

$$\phi_{s1} = \phi_1 + |\theta_o| \quad \text{for } |V_o| \angle \theta_o \text{ lags } |V_s| \angle 0 \quad (14)$$

Using Eq. (5), Eq. (13) and Eq. (14), we deduce

$$\phi_{s1} = \phi_1 - \theta_o \quad \text{for } -\pi < \theta_o < \pi \quad (15)$$

Fig. 4. The illustration diagram for the ROD control method.

This section will verify that the smart load power angle and its apparent power (power amplitude) can be separately controlled by the orbital-ES and radial-ES voltages, respectively, in the ROD control method. The illustration diagram of the invented ROD method is shown in Fig. 4. The details of the analysis will be discussed as follows.

A. Effect of the Orbital-ES Component

In order to investigate how the orbital-ES component affects the system, consider a condition that the radial-ES component is absent while the magnitude of the grid voltage is assumed equal to the nominal reference value $|V_{s_Ref}|$. The magnitude of the non-critical load voltage and the grid voltage are always equal under the orbital-ES control scheme, which is

$$|V_s| = |V_o| = |V_{s_Ref}|. \quad (16)$$

We defined the reference apparent power $|S_{o_Ref}|$ is considered as the apparent power of the non-critical load working at the nominal voltage $|V_{s_Ref}|$, which gives

$$|S_{o_Ref}| = \frac{|V_{s_Ref}|^2}{|Z_1|}. \quad (17)$$

Since the apparent power of the non-critical load in orbital-ES control scheme (where the radial component is absent) is

$$|S_1| = \frac{|V_o|^2}{|Z_1|} = \frac{|V_{s_Ref}|^2}{|Z_1|} = |S_{o_Ref}|, \quad (18)$$

hence, the complex power of the non-critical load is

$$\vec{S}_1 = |S_1| \angle \phi_1 = |S_{o_Ref}| \angle \phi_1. \quad (19)$$

The current of the non-critical load (which is the same with the current of the smart load) is

$$|I_1| = \frac{|V_o|}{|Z_1|} = \frac{|V_{s_Ref}|}{|Z_1|}. \quad (20)$$

Using Eq. (12), Eq. (16) and (20), the apparent power of the smart load can be written as

$$|S_{s1}| = |V_s||I_1| = \frac{|V_{s_Ref}|^2}{|Z_1|} = |S_{o_Ref}|, \quad (21)$$

hence, from Eq. (15) and (21), the complex power of the smart load is

$$\vec{S}_{s1} = |S_{s1}|\angle\phi_{s1} = |S_{o_Ref}|\angle(\phi_1 - \theta_o). \quad (22)$$

Consider that, initially, the orbital-ES is turned off, the angle θ_o is zero in accordance with Eq. (11). The complex power of the smart load and the non-critical are equal if the angle θ_o is zero as indicated in Eq. (19) and (22). After the orbital-ES is turned on and according to Eq. (22), the apparent power of the smart load keep unchanged and is always equal to the reference apparent power $|S_{o_Ref}|$. However, the power angle of the smart load changed from ϕ_1 to $(\phi_1 - \theta_o)$. Therefore, This proves that the apparent power of the smart load is always equal to the reference apparent power and is independent of the orbital-ES voltage while the power angle of the smart load can be adjusted by the orbital-ES voltage. The details of the effect on the smart load power angle and the complex power are discussed as follows.

Fig. 5. The angle θ_o versus the angle θ_{eso} .

1) Variation on Smart Load Power Angle: Consider the power angle of the smart load ϕ_{s1} , Eq. (11) and (15) imply that the angle ϕ_{s1} and θ_o are controlled by the angle θ_{eso} . The angle θ_o versus the angle θ_{eso} is plotted in Fig. 5 using Eq. (11). The positive change of the angle θ_{eso} causes the negative change of the angle θ_o and vice versa. Combining Eq. (11) and (15) gives

$$\phi_{s1} = \phi_1 - \text{sgn}(\theta_{eso})(2|\theta_{eso}| - \pi) \quad (23)$$

To realize how the orbital-ES component controls the power angle of the smart load, three plots are shown in Fig 6 using Eq. (23), which illustrates three example situations when the non-critical load is passive resistive load (Fig. 6(a)), passive resistive-inductive load (Fig. 6(b)) and passive resistive-capacitive load (Fig. 6(c)). Therefore, the above analysis shows that we can adjust the smart load power angle to a desired value using the orbital-ES voltage without changing the apparent power of the smart load.

Fig. 6. The power angle of smart load versus the angle of the orbital component.

2) *Variation on Smart Load Complex Power:* In the view of the power conversation, the following power equation will be hold in the orbital-ES component control

$$\vec{S}_{s1} = \vec{S}_1 + \vec{S}_{eso}. \quad (24)$$

Since the complex power of the non-critical load is always unchanged in accordance with Eq. (19), the change of the complex power of the smart load $\Delta \vec{S}_{s1}$ will be equal to that of the orbital-ES component $\Delta \vec{S}_{eso}$, which can be expressed using Eq. (19) and (22), as

$$\Delta \vec{S}_{s1} = \Delta \vec{S}_{eso} = |S_{o_Ref}| \angle (\phi_1 - \theta_o) - |S_{o_Ref}| \angle \phi_1. \quad (25)$$

Therefore, the net change of the real and reactive powers of the smart load and those of the orbital-ES are

$$\begin{aligned} \Delta P_{s1} &= \Delta P_{eso} = \text{Re}\{|S_{o_Ref}| \angle (\phi_1 - \theta_o)\} - \text{Re}\{|S_{o_Ref}| \angle \phi_1\} \\ &= |S_{o_Ref}| [\cos(\phi_1 - \theta_o) - \cos(\phi_1)] \\ &= -2|S_{o_Ref}| \sin\left(\frac{\theta_o}{2}\right) \sin\left(\frac{2\phi_1 - \theta_o}{2}\right) \end{aligned} \quad (26)$$

and

$$\begin{aligned} \Delta Q_{s1} &= \Delta Q_{eso} = \text{Im}\{|S_{o_Ref}| \angle (\phi_1 - \theta_o)\} - \text{Im}\{|S_{o_Ref}| \angle \phi_1\} \\ &= |S_{o_Ref}| [\sin(\phi_1 - \theta_o) - \sin(\phi_1)] \\ &= -2|S_{o_Ref}| \sin\left(\frac{\theta_o}{2}\right) \cos\left(\frac{2\phi_1 - \theta_o}{2}\right) \end{aligned} \quad (27)$$

To illustrate the effect of the orbital-ES on the variation of the smart load complex power, consider an example that a resistive-inductive load with power angle ϕ_1 is used as a non-critical load. Initially, the orbital-ES is turned off. The complex power vectors of the non-critical load and that of the smart load are equal, which is shown in Fig. 7(a), where those two power vectors overlap. After the orbital-ES is turned on, the positive change of the angle θ_{eso} causes the negative change of θ_o as shown in Fig. 7(b). Hence, the power factor of the smart load increases to $|\phi_1| + |\theta_o|$ according to Eq. (14). As a result, the real power of the smart load reduced from $\text{Re}(\vec{S}_1)$ to $\text{Re}(\vec{S}_{s1})$,

Fig. 7. The changes of complex power vector of the smart load due to the effect of the orbital-ES component.

according to Eq. (26), while the reactive power of the smart load increased from $\text{Im}(\vec{S}_1)$ to $\text{Im}(\vec{S}_{s1})$, according to Eq. (27). On the other hand, as shown in Fig. 7(c), the negative change of the angle θ_{eso} causes the positive change of θ_o and hence the power angle of the smart load reduce to $|\phi_1| - |\theta_o|$ according to Eq. (13). Thus, the real power of the smart load increased from $\text{Re}(\vec{S}_1)$ to $\text{Re}(\vec{S}_{s1})$ while the reactive power of the smart load reduced from $\text{Im}(\vec{S}_1)$ to $\text{Im}(\vec{S}_{s1})$. Unlike the direct-quadrature (DQ) decomposition method [19], where the real and reactive powers can be controlled independently using two DC state variables, the proposed orbital-ES component control method adjust the real and reactive power of the smart load simultaneously in such a way that the the power angle of the smart load can be controlled by the orbital-controlled ES.

B. Effect of the Radial-ES Component

Consider a condition that the orbital-ES component is absent and the grid voltage is assumed equal to the nominal reference voltage $|V_{s,Ref}|$. In the radial-ES control scheme, a voltage $|V_{esr}|$ is generated by the ES. The voltage is either in-phase or anti-phase with the non-critical load voltage such that $\theta_{esr} = \theta_o$ or $\theta_{esr} = (\theta_o - \pi)$, respectively. Hence, the angle θ_o is zero. That is

$$\theta_o = 0 \quad (28)$$

and also from Eq. (3),

$$\theta_{esr} = \begin{cases} 0 & \text{for } |V_o| \leq |V_s| \\ -\pi & \text{for } |V_o| > |V_s| \end{cases} \quad (29)$$

Besides, from Eq. (15) and (28), we deduced the smart load power angle ϕ_{s1} is always equal to the power angle of the non-critical load ϕ_1 in radial-ES control, which can be written as

$$\phi_{s1} = \phi_1. \quad (30)$$

In our following analysis, we defined the voltage vector $\overrightarrow{V_{esr}}$ as

$$\overrightarrow{V_{esr}} = \begin{cases} +|V_{esr}| & \text{for } \theta_{esr} = \theta_o \\ -|V_{esr}| & \text{for } \theta_{esr} = (\theta_o - \pi) \end{cases} \quad (31)$$

such that the magnitude of the non-critical load voltage is

$$|V_o| = |V_{s_Ref}| - \overrightarrow{V_{esr}}. \quad (32)$$

Using Eq. (32), the the smart load current is

$$\begin{aligned} |I_1| &= \frac{|V_o|}{|Z_1|} \\ &= \frac{|V_{s_Ref}| - \overrightarrow{V_{esr}}}{|Z_1|}, \end{aligned} \quad (33)$$

hence, using Eq. (32) and Eq. (33), the apparent power of the smart load $|S_{s1}|$, the apparent power of the non-critical load $|S_1|$ and the apparent power of the radial-ES component $|S_{esr}|$ are

$$\begin{aligned} |S_{s1}| &= |V_{s_Ref}| |I_1| \\ &= \frac{|V_{s_Ref}| (|V_{s_Ref}| - \overrightarrow{V_{esr}})}{|Z_1|}; \end{aligned} \quad (34)$$

$$\begin{aligned} |S_1| &= |V_o| |I_1| \\ &= \frac{(|V_{s_Ref}| - \overrightarrow{V_{esr}})^2}{|Z_1|}; \end{aligned} \quad (35)$$

$$\begin{aligned} |S_{esr}| &= \overrightarrow{V_{esr}} |I_1| \\ &= \frac{\overrightarrow{V_{esr}} (|V_{s_Ref}| - \overrightarrow{V_{esr}})}{|Z_1|}. \end{aligned} \quad (36)$$

Assumed that the magnitude $|V_{esr}|$ is ranged from 0 to $|V_{s_Ref}|$, the complex powers of the smart load, the non-critical load and the power of the radial-ES versus the vector $\overrightarrow{V_{esr}}$ are plotted in Fig. 8. It is noted that the

Fig. 8. The apparent power $|S_{s1}|$ versus the vector $\vec{V}_{esr}$.

definition of the direction of those three complex power vectors follows the definition of the voltage vector $\vec{V}_{esr}$ indicated in Eq. (31).

When $\vec{V}_{esr} = 0$, The apparent power of the smart load $|S_{s1}|$ and that of the non-critical load $|S_1|$ are equal to the reference apparent power $|S_{o_Ref}|$, while the complex power of the radial-ES component $|S_{esr}|$ is zero, where $|S_{o_Ref}|$ is defined in Eq. (17). When $V_{esr} = -|V_{s_Ref}|$, the apparent power $|S_{s1}|$, $|S_1|$ and $|S_{esr}|$ are equal to $2|S_{o_Ref}|$, $4|S_{o_Ref}|$ and $2|S_{o_Ref}|$, respectively. However, $\vec{S}_{esr}$ is anti-phase with $\vec{S}_1$ and $\vec{S}_{s1}$. When $V_{esr} = +|V_{s_Ref}|$, the apparent power $|S_{s1}|$, $|S_1|$ and $|S_{esr}|$ are all equal to zero. Also, with reference to the figure, the complex power $\vec{S}_{s1}$ varies linearly with the voltage vector $\vec{V}_{esr}$.

In the above analysis we concluded that in the radial-ES control, the smart load power angle is always unchanged and equal to the ϕ_1 according to Eq. (30) while the apparent power of the smart load changed with the voltage $|V_{esr}|$ indicated in Eq. (34). The details on the effect on the change on the smart load complex power is discussed as follows.

In the view of the power conversation, the relationship between those three complex powers is

$$\vec{S}_{s1} = \vec{S}_1 + \vec{S}_{esr}. \quad (37)$$

Using the similar analysis method on the Section III-A, the changes of the complex power on the smart load $\Delta\vec{S}_{s1}$, the non-critical load $\Delta\vec{S}_1$ and the radial-ES component $\Delta\vec{S}_{esr}$ are

$$\begin{aligned}\Delta \vec{S}_{s1} &= \frac{|V_{s_Ref}|(|V_{s_Ref}| - \vec{V}_{esr})}{|Z_1|} \angle \phi_1 - |S_{o_Ref}| \angle \phi_1 \\ &= -\frac{\vec{V}_{esr} \cdot |V_{s_Ref}|}{|Z_1|} \angle \phi_1\end{aligned}\quad (38)$$

$$\begin{aligned}\Delta \vec{S}_1 &= \frac{(|V_{s_Ref}| - \vec{V}_{esr})^2}{|Z_1|} \angle \phi_1 - |S_{o_Ref}| \angle \phi_1 \\ &= \frac{(|V_{s_Ref}| - \vec{V}_{esr})^2 - |V_{s_Ref}|^2}{|Z_1|} \angle \phi_1\end{aligned}\quad (39)$$

$$\begin{aligned}\Delta \vec{S}_{esr} &= \frac{\vec{V}_{esr}(|V_{s_Ref}| - \vec{V}_{esr})}{|Z_1|} \angle \phi_1 - 0 \\ &= \frac{\vec{V}_{esr}(|V_{s_Ref}| - \vec{V}_{esr})}{|Z_1|} \angle \phi_1\end{aligned}\quad (40)$$

(a) The vector $\vec{S}_{s1}$ is equal to $\vec{S}_1$ when $\vec{V}_{esr}$ is zero. (b) The magnitude of the vector $\vec{S}_{s1}$ is smaller than $|S_{o_Ref}|$ when $\vec{V}_{esr}$ is positive.

(c) The magnitude of the vector $\vec{S}_{s1}$ is larger than $|S_{o_Ref}|$ when $\vec{V}_{esr}$ is negative.

Fig. 9. The changes of complex power vector of the smart load due to the effect of the radial-ES.

To illustrate the effect of the radial-ES component on the variation of the smart load powers, consider an example that a non-critical resistive-inductive load with power angle ϕ_1 is used as a non-critical load. Initially, the radial-ES

is turned off. The complex power vectors of the non-critical load and that of the smart load are equal, which is shown in Fig. 9(a). After the radial-ES is turned on, the positive change of the vector $\vec{S}_{est}$ causes the decrease in the magnitude of the vector $\vec{S}_{s1}$ as shown in Fig. 9(b). Hence, the apparent power of the smart load decreases. As a result, the real and reactive powers of the smart load reduced from $\text{Re}(\vec{S}_1)$ to $\text{Re}(\vec{S}_{s1})$ and $\text{Im}(\vec{S}_1)$ to $\text{Im}(\vec{S}_{s1})$, respectively. On the other hand, as shown in Fig. 9(c), the negative change of the vector $\vec{S}_{est}$ causes the increase in the magnitude of the vector $\vec{S}_{s1}$. Thus, the real and reactive powers of the smart load increased from $\text{Re}(\vec{S}_1)$ to $\text{Re}(\vec{S}_{s1})$ and $\text{Im}(\vec{S}_1)$ to $\text{Im}(\vec{S}_{s1})$, respectively. It is noted the power angle of the smart load is maintained at unchange during the radial-ES control. Similar to the orbital-ES control, both the real and reactive power of the smart load change simultaneously in radial-ES control scheme.

IV. EXPERIMENTAL RESULTS

The Experiment is divided into two parts. In part one, the steady-state timing waveforms of the system is analyzed. Different radial and orbital ES voltages are applied to the system to validate the characteristic of the proposed ES voltage decomposition method. In part two, the time random-varying supply side voltage is used. This experiment is used to validate the ability of the ES regulating both the grid voltage and power angle of the smart load by the proposed ES voltage decomposition method.

A. Part One - Steady State Timing Waveforms

Fig. 10. The experiment setup of the orbital-ES control.

1) Orbital-ES Control Experiment: The purpose of this experiment is to explore the characteristic of the system with an orbital-ES installed. The experiment setup is shown in Fig. 10, in which the grid voltage is maintained at constant $|V_{s_Ref}| = 220 \text{ V} \angle 0^\circ$ at 50 Hz and the reference angle θ_{o_Ref} is used to control the phase and voltage of the orbital ES voltage in an open loop manner. The orbital controller is used to generate a control signal to the orbital-ES with a reference input signal θ_{o_Ref} implemented using Eq. (11). The impedance of the non-critical load is $R_1 + jX_1 = 51.35 + j38.51\Omega$ with a power angle 36.87° , in which the displacement power factor is $\cos(36.87^\circ) = 0.8$. At the beginning of the experiment, the ES is turned off. It is expected that with the ES turned off, the apparent power of the smart load is

$$\vec{S}_{s1} = |S_{s1}| \angle \phi_{s1} = \frac{220^2}{|51.35 + j38.51|} \angle (36.87^\circ) = 754 \text{ VA} \angle 36.87^\circ. \quad (41)$$

Fig. 11. The ES is turned off. (Yellow: non-critical load voltage, $V_o(t)$; Blue: smart load current, $I_{s1}(t)$; Red: grid voltage, $V_s(t)$; Green: ES voltage, $V_{es}(t)$)

(a) The orbital-ES is turned on by setting θ_{o_Ref} set to $+10^\circ$. (b) The orbital-ES is turned on by setting θ_{o_Ref} set to -10° .

Fig. 12. The steady-state timing waveforms of the system in orbital-ES control. (Yellow: non-critical load voltage, $V_o(t)$; Blue: smart load current, $I_{s1}(t)$; Red: grid voltage, $V_s(t)$; Green: ES voltage, $V_{es}(t)$)

The measured steady-state timing waveforms with ES turned off are shown in Fig. 11.

The orbital-ES is then turned on by setting the reference angle θ_{o_Ref} set to $+10^\circ$. From Eq. (11), the corresponding orbital-ES voltage is

$$\begin{cases} \theta_{eso} = f_{\theta-orbital}(+10^\circ) = -\text{sgn}(+10^\circ) \cdot \frac{180^\circ - |+10^\circ|}{2} = -85^\circ \\ V_{eso} = f_{V-orbital}(+10^\circ) = \sqrt{2|220|^2(1 - \cos(10^\circ))} = 38.3 \text{ V} \end{cases} \quad (42)$$

From Eq. (22), the complex power of the smart load is

$$\vec{S}_{s1} = |S_{s1}| \angle \phi_{s1} = \frac{220^2}{|51.35 + j38.51|} \angle (36.87^\circ - (10^\circ)) = 754 \text{ VA} \angle 26.87^\circ. \quad (43)$$

Fig. 12(a) shows the measured waveforms and data, the non-critical load voltage leads the grid voltage while the magnitude of them are maintained at around the nominal reference voltage 220 V, which follows Eq. (16). The measured apparent power of the load is 757.9 AV, which is in line with Eq. (43) (less than 1 % error) and is the same with that before the orbital-ES turned on. The measured power factor of the smart load changed to 0.891, hence the power angle is $\arccos(0.891) = 27^\circ$, which is closed to the calculated value 26.87° . The observation is in line with Eq. (22).

On the other hand, if the reference angle θ_{o_Ref} set to -10° . From Eq. (11), the corresponding orbital-ES voltage is

$$\begin{cases} \theta_{eso} = f_{\theta_orbital}(-10^\circ) = -\text{sgn}(+10^\circ) \cdot \frac{180^\circ - |-10^\circ|}{2} = 85^\circ \\ V_{eso} = f_{V_orbital}(-10^\circ) = \sqrt{2|220|^2(1 - \cos(10^\circ))} = 38.3 \text{ V} \end{cases} \quad (44)$$

From Eq. (22), the complex power of the smart load is

$$\vec{S}_{s1} = |S_{s1}| \angle \phi_{s1} = \frac{220^2}{|51.35 + j38.51|} \angle (36.87^\circ + (10^\circ)) = 754 \text{ VA} \angle 46.87^\circ. \quad (45)$$

Figure 12(b) shows the measured waveforms and data, the non-critical load voltage lags the grid voltage while the magnitude of them are maintained at around 220 V, which follows Eq. (16). The measured apparent power of the load is 749.6 AV, which is in line with Eq. (45) and is around the same with that before the orbital-ES turned on. The measured power factor of the smart load changed to 0.690, hence the power angle is $\arccos(0.690) = 46.4^\circ$. This is in line with Eq. (19) and (22).

The above experiment revealed that the power angle of the smart load can decrease from 36.87° to 26.87° if the orbital-ES is turned on by setting a positive angle $\theta_{o_Ref} = +10^\circ$. Similarly, the power angle of the smart load can increase from 36.87° to 46.87° if the orbital-ES is turned on by setting a negative angle $\theta_{o_Ref} = -10^\circ$. The apparent power of the smart load can be maintained at constant 754 AV when the power angle changes. The results are in good agreement with the discussion in Section III-A.

Fig. 13. The experiment setup of the radial control.

2) *Radial-ES Control Experiment:* The experiment setup for the radial-ES control is shown in Fig. 13. The output of the radial-ES controller is used to control the radial-ES voltage with a reference voltage V_{esr_Ref} . The phasor

angle of the radial-ES voltage is synchronized with the non-critical load voltage (either in-phase or anti-phase). The grid voltage and the non-critical load impedance are the same with the Section IV-A1 such that the initial complex power of the smart load before the ES turned on is follows Eq. (41).

(a) The radial-ES is turned on and its voltage is +50 V with a voltage in-phase with the non-critical load voltage. (b) The radial-ES is turned on and its voltage is -50 V with a voltage anti-phase with the non-critical load voltage.

Fig. 14. The steady-state timing waveforms of the system in radial-ES control. (Yellow: non-critical load voltage, $V_o(t)$; Blue: smart load current, $I_{s1}(t)$; Red: grid voltage, $V_s(t)$; Green: ES voltage, $V_{es}(t)$)

The radial-ES is then turned on and its voltage is at +50 V $\angle 0^\circ$ by setting $V_{esr_Ref} = +50$ V. The non-critical load voltage is in-phase with the grid voltage. The magnitude of the non-critical load voltage changed to around 170 V. From Eq. (30) and (34), the complex power of the smart load is

$$|S_{s1}| \angle \phi_{s1} = \frac{220(220 - 50)}{|51.35 + j38.51|} \angle 36.87^\circ = 582 \text{ AV} \angle 36.87^\circ. \quad (46)$$

Figure 14(a) shows the measured waveforms and data, the measured apparent power of the smart load decreased to 575.1 VA, which is around the same with the calculated result shown in Eq. (46). The measured power factor is 0.809 which is around the same with that before ES turned on.

In contrast, Fig. 14(b) shows the simulated waveforms, in which the magnitude of the radial-ES voltage is -50 V $\angle 0^\circ$ by setting $V_{esr_Ref} = -50$ V. The non-critical load voltage is anti-phase with the grid voltage. The magnitude of the non-critical load voltage changed to 270 V. From Eq. (30) and (34), the complex power of the smart load is

$$|S_{s1}| \angle \phi_{s1} = \frac{220(220 + 50)}{|51.35 + j38.51|} \angle 36.87^\circ = 925 \text{ AV} \angle 36.87^\circ. \quad (47)$$

Figure 14(b) shows the measured waveforms and data, the measured apparent power of the smart load increased

Fig. 15. The simplified schematic for the ROD regulation control.

Fig. 16. The simplified electrical system for the simulation with a time varying supply side voltage.

to 951.1 VA, which is around the same with the calculated result shown in Eq. (47). The measured power factor is 0.811 which is around the same with that before ES turned on.

The above experiment revealed that the apparent power of the smart load can decrease from 754 AV to 582 AV if the radial-ES is turned on with a positive voltage $+50 \text{ V} \angle 0^\circ$. Similarly, the apparent power of the smart load can increase from 754 AV to 925 AV if the radial-ES is turned on with a negative voltage $-50 \text{ V} \angle 0^\circ$. On the other hand, the power factor of the smart load can be maintained constant at around 0.8 when the apparent power changes. The results are in good agreement with the discussion in Section III-B.

B. Part Two - Time-Varying Supply Side Voltage

This part of the experiment validates the proposed ROD control method for ES can regulate the grid voltage and power factor of the smart load independently when a time-varying supply side voltage is present. The control schematic in this experiment is shown in Fig. 15. The configuration of the emulated power system is shown in

Fig. 17. Simulation waveforms with a time varying supply side voltage. (In the second figure: Red: ES voltage; Blue: Non-critical load voltage)

Fig. 16. The transmission line impedance is chosen to be $Z_t = (2 + j6.28)\Omega$. The critical load resistance is chosen to be $Z_1 = 76.90\Omega$, which consume a nominal real power of 629.39 W at $|V_s| = 220$ V. In order to realize the displacement power factor correction ability of the orbital-ES, an inductive load with an impedance of $Z_1 = (51.73 + j40.72)\Omega$ is used, which consume a nominal real power of 578.22 W at $|V_s| = 220$ V. The objective of this experiment is to validates the orbital-ES can be use for improving the power factor of this power system while the radial-ES is used to regulate the grid voltage.

The nominal supply side voltage is found by

$$|V_g|_{\text{nom}} = 220 \frac{|(Z_1 \angle \phi_1 // Z_2 \angle \phi_2) + Z_t \angle \phi_t|}{|Z_1 \angle \phi_1 // Z_2 \angle \phi_2|} \quad (48)$$

which gives,

$$|V_g|_{\text{nom}} = 249.8 \text{ V} \quad (49)$$

The supply side voltage fluctuations, simulating the situation of the future smart grid system with a large portions of intermittence power sources installed, is emulated by a random voltage source ΔV_g where the magnitude randomly changes from -5 V to 5V, such that the magnitude of the supply side voltage will vary randomly and hence

$$|V_g| = |V_g|_{\text{nom}} + \Delta V_g \quad (50)$$

The experiment is divided into four durations. From $t = 0$ to 300 s, the ES is turned off. From $t = 300$ to 600 s, the ES with orbital control is turned on with the reference angle θ_{o_Ref} is set to 10° . From $t = 600$ to 900 s, the ES with radial control is turned on with a grid reference voltage is set to 220 V. During $t = 900$ to 1200 s, both the orbital and radial controls are combined. The reference angle θ_{o_Ref} is set to 10° while the grid reference voltage is set to 220 V.

The experiment result is shown in Fig. 17. From $t = 0$ to 300 s, the ES is turned off. The grid voltage V_s is unregulated and the power factor of the smart load is

$$\cos(\phi_1) = \cos \left[\arctan \left(\frac{40.72}{51.73} \right) \right] = \cos(38.2^\circ) = 0.786. \quad (51)$$

From $t = 300$ to 600 s, the orbital ES is turned on. The grid voltage V_s is still kept unregulated but the power angle of the smart load improved by 10° . hence, the power factor of the smart load, according to Eq. (15) is

$$\cos(\phi_{s1}) = \cos(\phi_1 - \theta_o) = \cos(38.2^\circ - 10^\circ) = 0.881. \quad (52)$$

From $t = 600$ to 900 s, the ES is turned on with radial control. The grid voltage is regulated at 220 V. Since the phase of the radial ES voltage is either in-phase or anti-phase with the non-critical load voltage such that the power factor of the smart load is not affect and is maintained at 0.786. From $t = 900$ to 1200 s, the ES is turned on with both the radial and orbital control. Both the power factor improvement and grid voltage regulation are performed simultaneously. The power factor of the smart load can be improved to 0.881 while the grid voltage can be regulated at around 220 V.

It is concluded that from $t = 600$ to 1200 s, the smart load apparent power is kept changing along with the fluctuation of the supply side voltage in such a way that the load shedding or boosting can be achieved. Furthermore, from $t = 300$ to 600 s and $t = 900$ to 1200 s, the power factor of the smart load can improved from 0.786 to 0.881. As a result, the grid voltage regulation process can be done by using radial ES control while the power quality of this power transmission system will not be affected by the regulation process using orbital control.

REFERENCES

- [1] S. Wang and G. yuan Han, "Research on energy crisis and corresponding policies in heilongjiang province," in *Artificial Intelligence, Management Science and Electronic Commerce (AIMSEC), 2011 2nd International Conference on*, 2011, pp. 544–547.
- [2] A. Sadrul Ula, "Global warming and electric power generation: What is the connection?" *Energy Conversion, IEEE Transactions on*, vol. 6, no. 4, pp. 599–604, 1991.
- [3] A. Glaser, "After fukushima: Preparing for a more uncertain future of nuclear power," *Engineering Management Review, IEEE*, vol. 39, no. 4, pp. 19–27, 2011.
- [4] "2011 renewable energy sources in figures," Federal Ministry for the Environment, Nature Conservation and Nuclear Safety (BMU), Public Relations Division, July 2012.
- [5] "China eyes 20% renewable energy by 2020," *China Daily*, Jun. 10 2009.
- [6] D. Levitan, "Ieee spectrum - 2012 renewable energy recap: Renewables reality check," Dec. 2012. [Online]. Available: <http://spectrum.ieee.org/energywise/energy/renewables/2012-renewable-energy-recap-renewables-reality-check>
- [7] A.-H. Mohsenian-Rad, V. Wong, J. Jatskevich, R. Schober, and A. Leon-Garcia, "Autonomous demand-side management based on game-theoretic energy consumption scheduling for the future smart grid," *Smart Grid, IEEE Transactions on*, vol. 1, no. 3, pp. 320–331, 2010.
- [8] M. Parvania and M. Fotuhi-Firuzabad, "Demand response scheduling by stochastic scuc," *Smart Grid, IEEE Transactions on*, vol. 1, no. 1, pp. 89–98, 2010.
- [9] M. Pedrasa, T. Spooner, and I. MacGill, "Scheduling of demand side resources using binary particle swarm optimization," *Power Systems, IEEE Transactions on*, vol. 24, no. 3, pp. 1173–1181, 2009.
- [10] A. Conejo, J. Morales, and L. Baringo, "Real-time demand response model," *Smart Grid, IEEE Transactions on*, vol. 1, no. 3, pp. 236–242, 2010.
- [11] A.-H. Mohsenian-Rad and A. Leon-Garcia, "Optimal residential load control with price prediction in real-time electricity pricing environments," *Smart Grid, IEEE Transactions on*, vol. 1, no. 2, pp. 120–133, 2010.
- [12] A. Roscoe and G. Ault, "Supporting high penetrations of renewable generation via implementation of real-time electricity pricing and demand response," *Renewable Power Generation, IET*, vol. 4, no. 4, pp. 369–382, 2010.
- [13] F. Kienzle, P. Ahcin, and G. Andersson, "Valuing investments in multi-energy conversion, storage, and demand-side management systems under uncertainty," *Sustainable Energy, IEEE Transactions on*, vol. 2, no. 2, pp. 194–202, 2011.
- [14] S. C. Lee, S. Kim, and S. Kim, "Demand side management with air conditioner loads based on the queuing system model," *Power Systems, IEEE Transactions on*, vol. 26, no. 2, pp. 661–668, 2011.
- [15] G. C. Heffner, C. Goldman, and M. Moezzi, "Innovative approaches to verifying demand response of water heater load control," *Power Delivery, IEEE Transactions on*, vol. 21, no. 1, pp. 388–397, 2006.
- [16] A. Brooks, E. Lu, D. Reicher, C. Spirakis, and B. Weihi, "Demand dispatch," *Power and Energy Magazine, IEEE*, vol. 8, no. 3, pp. 20–29, 2010.
- [17] S. Y. Hui, C. K. Lee, and F. Wu, "Electric springs - a new smart grid technology," *Smart Grid, IEEE Transactions on*, vol. 3, no. 3, pp. 1552–1561, 2012.
- [18] S.-C. Tan, C. K. Lee, and S. Hui, "General steady-state analysis and control principle of electric springs with active and reactive power compensations," *Power Electronics, IEEE Transactions on*, vol. 28, no. 8, pp. 3958–3969, 2013.
- [19] R. Park, "Two-reaction theory of synchronous machines generalized method of analysis-part i," *American Institute of Electrical Engineers, Transactions of the*, vol. 48, no. 3, pp. 716–727, 1929.