Two layer electrified pressure-driven flow in topographically structured channels

Elizaveta Dubrovina¹, Richard V. Craster¹ and Demetrios T. Papageorgiou^{1†}

¹Department of Mathematics, Imperial College London, London SW7 2AZ, UK

(Received xx; revised xx; accepted xx)

The flow of two stratified viscous immiscible perfect dielectric fluids in a channel with topographically structured walls is investigated. The flow is driven by a stream wise pressure gradient and an electric field across the channel gap. This problem is explored in detail by deriving and studying a nonlinear evolution equation for the interface valid for large amplitude long waves in the Stokes flow regime. For flat walls the electrified flow is long-wave unstable with a critical cut-off wavenumber that increases linearly with the magnitude of the applied voltage. In the nonlinear regime it is found that the presence of pressure-driven flow prevents electrostatically induced interface touchdown that has been observed previously - time modulated nonlinear travelling waves emerge instead. When topography is present, linearly stable uniform flows become non-uniform spatially periodic steady states; a small amplitude asymptotic theory is carried out and compared with computations. In the linearly unstable regime intricate nonlinear structures emerge that depend, among other things, on the magnitude of the wall corrugations. For a low amplitude sinusoidal boundary, time modulated travelling waves are observed that are similar to those found for flat walls but are influenced by the geometry of the wall and slide over it without touching. The flow over a high amplitude sinusoidal pattern is also examined in detail and it is found that for sufficiently large voltages the interface evolves to large amplitude waves that span the channel and are subharmonic relative to the wall. A type of “walking” motion emerges that causes the lower fluid to wash through the troughs and create strong vortices over the peaks of the lower boundary. Nonuniform steady states induced by the topography are calculated numerically for moderate and large values of the flow rate, and their stability is analysed using Floquet theory. The effect of large flow rates is also considered asymptotically to find solutions that compare very well with numerical computations.

1. Introduction

Thin liquid films appear in a wide variety of applications ranging from large scale geophysical flows, such as lava flows, to small scale microfluidic devices, such as lab-on-chip technology (see Craster & Matar 2009; Toner & Irimia 2005; SooHoo & Walker 2009). In the present study, we consider pressure-driven two-layer flows through channels of variable cross-section that are additionally influenced by the presence of electric fields arising from imposing a constant voltage potential across the channel walls. Sufficiently strong electric fields can destabilise the flow and lead to nonlinear free surface patterns that can be useful in applications, e.g. micro-lithography. The reader is referred to Melcher & Taylor (1969); Saville (1997) for general reviews of electrohydrodynamics.

In recent years there has been growing interest in the miniaturisation of electronic tools

† Email address for correspondence: d.papageorgiou@imperial.ac.uk

and much research has gone into finding appropriate techniques to pattern polymers. Details on the applications and techniques of polymer patterning can be found in the review by Nie & Kumacheva (2008). One such technique exploits the electrohydrodynamic instabilities of a system to induce ordered patterns and it was first explored in two experimental papers contemporary to each other (see Chou & Zhuang 1999; Schaffer *et al.* 2000). Since then, electrohydrodynamic instability induced structures have been the focus of much research due to the simplicity and the low cost of this patterning method, details of which can be found in the review by Wu & Russell (2009). Linear stability analyses have been conducted using both the perfect dielectric (Schaffer *et al.* 2001) and the leaky dielectric (Pease & Russell 2002) models. Both predict experimental data reasonably well, with the leaky dielectric decreasing pillar spacing and increasing their rate of formation.

Linear stability analyses and full numerical simulations have been done for a variety of similar setups. Ozen *et al.* (2006) and Li *et al.* (2007) considered the linear stability of the interface between two conducting fluids bounded by two flat electrodes at arbitrary Reynolds numbers, and found that the electric field has a destabilising effect for perfect dielectrics and either a stabilising or destabilising effect for leaky dielectrics with either Couette or Poiseuille base flows. A comparison of the instabilities observed when a horizontal or vertical electric field is acting, was considered by Uguz & Aubry (2008) for inertialess flows and horizontal fields were shown to be stabilizing while vertical ones lead to long wave instabilities. Craster & Matar (2005) carried out numerical simulations for a two-fluid system under a vertical electric field in the absence of flow, and showed that initially small perturbations developed into spatially periodic columnar structures. Thaokar & Kumaran (2005) considered electrified two-fluid Couette flows of equal viscosities at zero Reynolds numbers and present a detailed study of linear and weakly nonlinear stability as well as simulations using boundary integral methods; they find that the presence of shear is stabilizing in the sense that higher critical electric fields are required for instability, and subcritical bifurcations give way to supercritical ones. Direct numerical simulations of an equivalent problem with inertia present was carried out by Maehlmann & Papageorgiou (2011) who found that the interface evolves into fingerlike structures that were driven away from the centre line due to the presence of background flow. In this study we combine these setups and look at a pressure driven two layer flow between one flat and one sinusoidal electrode.

There has been some recent work on flow of fluids over surface topography in a setup similar to the one in this paper, mostly involving a fluid-air interface. Lenz & Kumar (2007) analysed steady states of the interface between two viscous fluids flowing between one flat boundary and one with periodic steps using lubrication theory. This set-up was later considered by Zhou & Kumar (2012) with full numerical simulations that showed good agreement with those from lubrication theory. Luo & Pozrikidis (2006) considered a similar setup but for a gravity-driven flow and with a sinusoidal lower wall and found the interfacial features to be in phase with the topography. Tseluiko *et al.* (2008) looked at steady solutions for the gravity-driven flow of a single layer of electrified viscous fluid over steps, trenches and mounds and showed that the presence of an electric field can alter some of the interfacial features. Heier *et al.* (2009) considered the instability of a polymer film under the action of a heterogeneous electric field caused by placing a sinusoidally shaped upper electrode above the film; they find theoretically and experimentally that below a critical value of the electric field a non-uniform steady state shape appears and at higher values an instability sets causing pillars to form and reach the upper electrode. Ramkrishnan & Kumar (2014) investigated the fluid-air interface in the flow between a patterned and a flat electrode with both perfect and leaky dielectric materials considered.

FIGURE 1. Schematic of the problem studied. The lower boundary is structured topographically with a given position $y = -z(x)$ and is held at constant voltage $V_2 = \tilde{V}_b$. The upper wall is at $y = \beta H$ and is held at zero potential.

They found that in the case of a perfect dielectric a small amplitude sinusoidal pattern leads to an interface shape that mimics the electrode pattern. Karapetsas & Bontozoglou (2015) carried out 2D numerical calculations for a Newtonian fluid and a viscoelastic polymeric fluid under a patterned mask to find that perturbations grow until they reach the top electrode and viscoelasticity affects their wavelength.

In the present study we extend previous work by considering two-fluid systems in channels of variable thickness and under the action of electric fields applied in the gap. Lubrication theory is used under negligible inertia conditions to derive an evolution equation that describes the nonlinear dynamics in this limit. Our objectives include the effect of the field in destabilising the flow and the coupling of such instabilities with non-zero applied flow rates; of particular interest is the ability of flow to prevent fluid layer thinning and interface touchdown, and the description of the resulting nonlinear dynamics as the flow rate changes. We note that in the absence of a field the inertialess flow is linearly stable for arbitrary viscosity ratios between the phases - see Yih (1967).

The article is structured as follows: §2 provides details of the governing equations and derives the long-wave model that is studied in detail. Section §3 presents results for flat walled channels and describes the effect of flow on pattern formation. Section §4 considers wavy wall effects and the resulting formation of stable and unstable wavy solutions. Section §5 considers the stability of non-uniform steady-states results using a Floquet analysis, and Section §6 studies large flow rate solutions numerically and asymptotically. Section §7 includes our conclusions.

2. Formulation

2.1. Governing equations

We consider the dynamics of two layers of immiscible viscous fluid that are placed between two electrodes, the top one is parallel to the undisturbed interface while the bottom electrode is patterned and its shape is given by $y = -z(x)$ (figure 1). The flow in the channel is driven by a pressure gradient and the overall flow rate through the channel is taken to be constant. The fluids are assumed to be perfect dielectrics and are placed in the regions $0 \leq y \leq \beta H$ (fluid 1) and $-z(x)H \leq y \leq 0$ (fluid 2) and the undisturbed interface lies at $y = 0$. The electrodes are kept at constant voltage potentials $V_1 = 0$ at the top and $V_2 = \tilde{V}_b$ at the bottom. The interface location is given by $y = h(x, t)$ and the interfacial tension constant and equal to γ .

The fluids are taken to be Newtonian and incompressible and the electric fields are governed by the electrostatic approximation of Maxwell's equations. Here we give the

general governing equations for the two fluids, assumed to be perfect dielectrics, and denoted as fluid 1 (upper) and fluid 2 (lower), and having viscosities $\mu_{1,2}$, densities $\rho_{1,2}$ and dielectric constants $\epsilon_{1,2}$, respectively. The velocity in fluid i (for $i = 1, 2$) is $\mathbf{u}_i = (u_i, v_i, 0)$ where u_i and v_i are the components in the x and the y direction respectively; P_i is the pressure in fluid i . Due to the small scale of the systems of interest here gravity can be neglected.

The fluid flow is governed by the Navier-Stokes and continuity equations in each region $i = 1, 2$

$$\rho_i(\mathbf{u}_{it} + \mathbf{u}_i \cdot \nabla \mathbf{u}_i) = -\nabla P_i + \mu_i \nabla^2 \mathbf{u}_i, \quad (2.1)$$

$$\nabla \cdot \mathbf{u}_i = 0. \quad (2.2)$$

The above equations are solved together with interfacial boundary conditions that correspond to continuity of the fluid velocity at the interface and jumps in the normal and tangential stresses:

$$[\mathbf{u} \cdot \mathbf{n}]_2^1 = [\mathbf{u} \cdot \mathbf{t}]_2^1 = 0, \quad [\mathbf{n} \cdot \mathbf{T} \cdot \mathbf{n}]_2^1 = \gamma \kappa, \quad \left[\mathbf{t} \cdot \mathbf{T}^{\mathbf{F}} \cdot \mathbf{n} \right]_2^1 = 0, \quad (2.3)$$

where $[(\cdot)]_2^1$ denotes the jump in $(\cdot)$ as the interface is crossed from above; $\mathbf{n} = (-h_x, 1)/\sqrt{1+h_x^2}$ is the outward pointing normal vector, $\mathbf{t} = (1, h_x)/\sqrt{1+h_x^2}$ is the tangent vector, and $\kappa = h_{xx}/(1+h_x^2)^{3/2}$ is the local curvature. The total stress tensor $\mathbf{T} = \mathbf{T}^{\mathbf{F}} + \mathbf{T}^{\mathbf{E}}$ has both a fluid part and an electrical part given by

$$\mathbf{T}^{\mathbf{F}} = -p\mathbf{I} + \mu(\nabla \mathbf{u} + \nabla \mathbf{u}^T), \quad \mathbf{T}^{\mathbf{E}} = \epsilon_i \left(\mathbf{E}\mathbf{E} - \frac{1}{2}|\mathbf{E}|^2 \mathbf{I} \right). \quad (2.4)$$

Note that the Maxwell stress contribution drops out of the tangential stress balance in (2.3) after use Gauss' law given below in (2.6)b. In addition, we have no slip and no penetration at both boundaries $y = -z(x)H$ and $y = \beta H$.

The electric field $\mathbf{E}_i$ is irrotational, hence it can be expressed by $\mathbf{E}_i = -\nabla V_i$ where the voltage potentials V_i are governed by Laplace equations

$$\nabla^2 V_i = 0. \quad (2.5)$$

The boundary conditions across the interface are those of continuity of V and continuity of the displacement field in the normal direction (the latter is Gauss's law),

$$V_1 = V_2, \quad [\epsilon \mathbf{E} \cdot \mathbf{n}]_2^1 = 0 \quad \text{on} \quad y = h(x, t). \quad (2.6)$$

At the walls the voltages are kept constant according to

$$V_1 = 0 \quad \text{at} \quad y = \beta H, \quad V_2 = \tilde{V}_b \quad \text{at} \quad y = -z(x)H. \quad (2.7)$$

To complete the system we need a kinematic condition at the interface

$$v_i = h_t + u_i h_x \quad \text{on} \quad y = h(x, t), \quad (2.8)$$

and an overall flow rate condition that is prescribed (the resulting horizontal pressure gradient comes as part of the solution)

$$\int_{h(x,t)}^{\beta H} u_1 dy + \int_{-z(x)}^{h(x,t)} u_2 dy = Q. \quad (2.9)$$

This set of nonlinear equations plus boundary conditions are a formidable nonlinear

system and to make progress we will utilise asymptotic methods to derive reduced dimension nonlinear evolution equations that are valid for thin films.

2.2. Dimensionless equations

The equations are non-dimensionalised using the following scales:

$$(x, y) = H(x', y'), \quad (u, v) = U(u', v'), \quad t = \frac{H}{U}t', \quad V = V_b V', \quad P = \frac{\mu_1 U}{H}P'. \quad (2.10)$$

Here U is a typical velocity scale, for example the velocity at the undisturbed interface of the equivalent straight walls channel, and the scale V_b will be chosen later in order to normalize to unity the coefficient of the electrical Maxwell stresses in the normal stress balance (2.15) below. The following non-dimensional equations emerge where for simplicity all dashes are dropped:

$$Re(u_{it} + u_i u_{ix} + v_i u_{iy}) = -P_{ix} + m_i(u_{ixx} + u_{iyy}), \quad (2.11)$$

$$Re(v_{it} + u_i v_{ix} + v_i v_{iy}) = -P_{iy} + m_i(v_{ixx} + v_{iyy}), \quad (2.12)$$

$$u_{ix} + v_{iv} = 0, \quad (2.13)$$

$$V_{ixx} + V_{iyy} = 0. \quad (2.14)$$

The dimensionless normal and tangential stress balances (see equation (2.3)) become, at $y = h(x, t)$,

$$\begin{aligned} & \left[-P_i + \frac{2}{1 + h_x^2} [m_i v_{iy}(1 - h_x^2) - m_i h_x(u_{iy} + v_{ix})] + \right. \\ & \left. + \bar{\epsilon}_i \frac{1 - h_x^2}{2(1 + h_x^2)} (V_{iy}^2 - V_{ix}^2) - \frac{2\bar{\epsilon}_i h_x}{1 + h_x^2} V_{ix} V_{iy} \right]_2 = \frac{h_{xx}}{\text{Ca}(1 + h_x^2)^{3/2}}. \end{aligned} \quad (2.15)$$

$$[4h_x m_i v_{iy} + (1 - h_x^2)(m_i u_{iy} + m_i v_{ix})]_2^1 = 0. \quad (2.16)$$

while the continuity of velocity at the interface, the kinematic condition and the overall flow rate condition (see (2.9)) transform to

$$u_1 = u_2, \quad v_1 = v_2, \quad \text{on } y = h(x, t), \quad (2.17)$$

$$v_{1,2} = h_t + u_{1,2} h_x, \quad \text{on } y = h(x, t), \quad (2.18)$$

$$\int_{h(x,t)}^{\beta} u_1 dy + \int_{-z(x)}^{h(x,t)} u_2 dy = \tilde{Q}. \quad (2.19)$$

The voltage continuity and Gauss law conditions (2.6) become, at $y = h(x, t)$,

$$V_1 = V_1, \quad [\bar{\epsilon}_i(h_x V_{ix} - V_{iy})]_2^1 = 0. \quad (2.20)$$

Finally the boundary conditions for the velocity and voltage at the upper and lower walls become

$$u_1 = 0, \quad V_1 = 0 \quad \text{at } y = \beta, \quad (2.21)$$

$$u_2 = 0, \quad V_2 = V_b \quad \text{at } y = -z(x). \quad (2.22)$$

In the process of the non-dimensionalisation the following dimensionless parameters emerge:

$$\begin{aligned} Re &= \frac{U \rho_1 H}{\mu_1}, & Ca &= \frac{U \mu_1}{\gamma}, & V_b &= \left(\frac{U \mu_1 L}{\epsilon_0} \right)^{1/2}, \\ m_i &= \frac{\mu_i}{\mu_1}, & \tilde{Q} &= \frac{Q}{UH}, & \bar{\epsilon}_i &= \frac{\epsilon_i}{\epsilon_0}. \end{aligned}$$

Here Re is the Reynolds number, Ca is the capillary number, V_b is the dimensionless voltage imposed at the lower wall $y = -z(x)$, $\tilde{Q}$ is the dimensionless flow rate, m_2 is the viscosity ratio of lower to upper fluid, and $\bar{\epsilon}_i$ are the relative electrical permittivities in each region with respect to that of free space ϵ_0 . We also note that the problem is solved subject to periodic boundary conditions in x when $z(x)$ is spatially periodic; in such cases the pressure gradient can be written as a constant plus a spatially periodic part of zero spatial mean.

2.3. Long-wave analysis and derivation of evolution equations

In the analysis that follows we assume that the wavelength λ of interfacial disturbances is long compared to the channel height H and take $\delta = H/\lambda \ll 1$. We make the following change of variables in each region $i = 1, 2$:

$$u_i = \tilde{u}_i, \quad v_i = \delta \tilde{v}_i, \quad x = \frac{\hat{x}}{\delta}, \quad t = \frac{\hat{t}}{\delta}, \quad P_i = \frac{\tilde{P}_i}{\delta}, \quad V_i = \tilde{V}_i. \quad (2.23)$$

For convenience the hats on the independent variables $\hat{x}$ and $\hat{t}$ are dropped. The scaling for the vertical velocities v_i comes from the continuity equations while the one for the pressures is needed for the flow to be driven by the pressure gradient at leading order (see for example Craster & Matar (2009) and references therein). In order to retain electric field and surface tension effects we are led to the canonical asymptotic limit of strong surface tension and high contrast permittivities in the two fluids, namely $Ca \sim \delta^3$ and $\bar{\epsilon}_i \sim 1/\delta$. Note that other limits are possible, for example weaker surface tension and comparable electrical permittivities $Ca \sim \delta^2$ and $\bar{\epsilon}_i \sim 1$, that can yield Benney type equations with small regularizing terms containing inertia - see Tseluiko & Papageorgiou (2006) for electrified falling films on flat substrates. In addition we take the Reynolds number to be small, $Re \sim \delta$, since we are interested in small scale geometries with applications in microfluidics. The solutions are expanded in powers of δ as follows

$$(\tilde{u}_i, \tilde{v}_i, \tilde{P}_i, \tilde{V}_i) = (u_i^{(0)}, v_i^{(0)}, p_i^{(0)}, V_i^{(0)}) + \delta (u_i^{(1)}, v_i^{(1)}, p_i^{(1)}, V_i^{(1)}) + O(\delta^2),$$

and at leading order the system (2.11)-(2.14) yields

$$m_i u_{iyy}^{(0)} = p_{ix}^{(0)}, \quad p_{iy}^{(0)} = 0, \quad u_{ix}^{(0)} + v_{iy}^{(0)} = 0, \quad V_{iyy}^{(0)} = 0. \quad (2.24)$$

The interfacial conditions (2.15)-(2.18) and (2.20) become, at leading order,

$$\begin{aligned} \left[-p_i^{(0)} + \bar{\epsilon}_i \frac{(V_{iy}^{(0)})^2}{2} \right]_2^1 &= h_{xx}, & [m_i u_{iy}^{(0)}]_2^1 &= 0, & [u_i^{(0)}]_2^1 &= 0, \\ [-\bar{\epsilon}_i V_{iyy}^{(0)}]_2^1 &= 0, & [V_i^{(0)}]_2^1 &= 0, \end{aligned} \quad (2.25)$$

while the overall flow rate condition (2.19) gives

$$\int_h^\beta u_1^{(0)} dy + \int_{-z}^h u_2^{(0)} dy = \tilde{Q}. \quad (2.26)$$

Solving (2.24) along with the interfacial conditions (2.25) and the boundary conditions (2.21)-(2.22) gives the following expressions for the horizontal velocities and the voltages,

$$u_1^{(0)} = \frac{p_{1x}^{(0)}}{2m_1}(y^2 - \beta^2) + f_1(x, t)(y - \beta), \quad u_2^{(0)} = \frac{p_{2x}^{(0)}}{2m_2}(y^2 - z^2) + f_2(x, t)(y + z), \quad (2.27)$$

$$V_1^{(0)} = d_1(x, t)(y - \beta), \quad V_2^{(0)} = d_2(x, t)(y + z) + V_b. \quad (2.28)$$

where $d_i(x, t)$, $f_i(x, t)$, $p_{ix}^{(0)}(x, t)$ for $i = 1, 2$ are functions of $h(x, t)$ and its derivatives - see appendix A for details. Finally, the kinematic condition is written in integral form using the continuity equation (2.14) as in (Papaefthymiou *et al.* 2013) for example:

$$h_t + \left(\int_{-z(x)}^{h(x, t)} u_2^{(0)} dy \right)_x = 0. \quad (2.29)$$

Substituting the leading order solutions (2.27)-(2.28) found above into (2.29) leads to the following evolution equation for the interfacial position $h(x, t)$:

$$h_t + \left\{ \frac{D_3}{6m_2} \left[D_4 p_{2x}^{(0)} + 3m_2 f_2 \right] \right\}_x = 0, \quad (2.30)$$

where $D_3 = (h(x, t) + z(x))^2$ and $D_4 = h(x, t) - 2z(x)$ (see appendix A for details of the functions involved). It should be stressed that once the interfacial amplitude $h(x, t)$ is determined, then the leading order flow and voltage potential throughout the channel follow from the solutions (2.27) and (2.28). Such expressions are used in the sequel when constructing instantaneous (or steady state) streamlines to visualise the flow and obtain information about the distribution of vorticity in the micro channel.

Equation (2.30) is solved numerically using spectral methods in space and the stiff ODE solver DASSL in time (see Petzold 1982). The latter is a Fortran package that approximates derivatives using backward differentiation formulas of order p with $1 \leq p \leq 5$; the order p and the time step size are selected adaptively in order to keep errors below a desired tolerance level. The discretization results in a large nonlinear system that is solved efficiently and accurately using a Newton's method. The initial condition used in our computations is

$$h(x, 0) = h_0 \cos(kx), \quad (2.31)$$

with $h_0 = 0.01$ (or $h_0 = 0$ when stated) and different values of the wavenumber k . The initial condition (2.31) is $\frac{2\pi}{k}$ -periodic and typically the evolution equation (2.30) is also solved on a periodic domain of length $2\pi/k$. We have also carried out computations on longer domains that are integer multiples of $2\pi/k$, in order to investigate the possibility of subharmonic instabilities. The numerical integration is carried out to large enough times to enable identification of the types of solutions that emerge.

2.4. Linear stability for flat boundaries

When the lower boundary is wavy, the base state is non-uniform and its stability is not amenable to a normal mode analysis - Floquet theory is used instead as detailed later in Section 5. To gain an understanding of the underlying instabilities present, in what follows we perform a linear stability analysis for a flat lower electrode placed at $y = -Z_c = 0.9$. Note that this analysis is a special case of that in Ozen *et al.* (2006) and Li *et al.* (2007) - it is the inertialess long-wave version of those studies and we include it for completeness and guidance for the wavy boundary nonlinear work that follows. In this case the evolution equation is linearized about the steady state $h \equiv 0$ and solutions

FIGURE 2. Linear growth rate for flat bottom walls at $y = -0.9$ and for an applied dimensionless voltage $V_b = 3$. Other parameters are the dimensionless flow rate $\tilde{Q} = 0.1$, $\beta = 1$ (i.e. the upper wall is at $y = 1$), dimensionless permittivities $\bar{\epsilon}_1 = 1$ and $\bar{\epsilon}_2 = 5$, and viscosity ratio $m_2 = 1$.

proportional to $\exp(ikx + st)$ are sought leading to a dispersion relation for the growth rate s as a function of the wavenumber k . Figure 2(a) shows the real part of s which is the growth rate, and panel (b) shows its imaginary part which is the frequency. This is done for a typical set of physical parameters with an imposed dimensionless voltage $V_b = 3$, a flow rate $\tilde{Q} = 0.1$, a unit channel height described by $\beta = 1$, relative permittivities $\bar{\epsilon}_1 = 1$ and $\bar{\epsilon}_2 = 5$, and equal viscosities so that $m_1 = m_2 = 1$. In order to reduce the large set of parameters that characterises our problem, we proceed with equal viscosities throughout the rest of the paper. The results show that the flow is long wave unstable with a finite band of unstable modes with short waves (large k) damped. In addition, the imaginary part of s is nonzero and in fact linear in k , hence linear waves are predicted to travel with a constant phase velocity. Hence we can expect that after nonlinear saturation the emerging structures will tend to travel in the direction of increasing x . The precise nature of the emerging coherent structures is undertaken next through detailed numerical computations.

3. Flat lower boundary: formation of directed assembly travelling wave structures

We begin our numerical studies by considering the case when the lower electrode is flat and placed at $y = -Z_c$ where $Z_c > 0$ is a constant. Figure 3(a) shows the interfacial deformation $h(x, t)$ at four consecutive relatively large times ensuring transients have died out; here $Z_c = 0.9$ so that the dimensionless channel thickness is 1.9 units, and the other parameters are as in figure 2 so that the $k = 1$ mode is unstable. The solid curve corresponds to $t = 200$, the dashed curve to $t = 200.6$, the dot-dashed curve to $t = 201.2$, and the dotted curve to $t = 201.8$. The linear instabilities saturate to what appear to be nonlinear travelling waves that span almost the whole extent of the channel. The interface approaches the boundaries but remains at a small but finite distance from them for the whole duration of the computation - such behaviour has been confirmed for much longer computations with times as large as 10^4 and different parameters. This is in contrast to situations with no background flow, i.e. $\tilde{Q} = 0$ in our notation, where electrostatic instabilities lead to interfacial contact with the wall - see for example the theoretical studies of Craster & Matar (2005), Tseluiko & Papageorgiou (2007b), Tseluiko & Papageorgiou (2007a), Barannyk *et al.* (2015) for both planar and cylindrical geometries as well as fields acting parallel to the undisturbed interface, as well

FIGURE 3. (a) Interface $h(x, t)$ at $t = 200$ (solid curve), $t = 200.6$ (dashed curve), $t = 201.2$ (dot dashed curve) and $t = 201.8$ (dotted curve). Walls are at $y = -0.9$ ($Z_c = 0.9$) and $y = 1$ ($\beta = 1$). Other parameters are, $\tilde{Q} = 1$, $V_b = 3$, $\bar{\epsilon}_1 = 1$, $\bar{\epsilon}_2 = 5$, $m_2 = 1$. (b) Minimum distance between the interface and the lower boundary at time $t = 300$ as the flow rate $\tilde{Q}$ varies.

as the experiments of Schaffer *et al.* (2001). In figure 3(b) we quantify these observations in the presence of flow by monitoring the minimum distance of the interface to the walls as $\tilde{Q}$ varies - to fix matters we do this for different runs and calculate minimal approaches at a large time $t = 300$. The results indicate that the minimum distance increases as $\tilde{Q}$ increases thus confirming the earlier findings that there is a flow-induced stabilisation of touchdown events. As mentioned already, when $\tilde{Q} = 0$ we expect asymptotic thinning with touchdown as $t \rightarrow \infty$, and the finite value of approximately 0.02 given in figure 3(b) reflects the fact that t is not large enough - larger t would lead to smaller values (see Craster & Matar (2005), Tseluiko & Papageorgiou (2007b) for example). Similar stabilising effects due to flow are found, for instance, when van der Waals forces are present that would otherwise cause film rupture (Bielarz & Kalliadasis (2003); Kalpathy *et al.* (2010); Davis *et al.* (2010)).

Even though the solutions presented in figure 3(a) appear to be nonlinear travelling waves, closer analysis of the data establishes that they are in fact travelling time-periodic waves - such structures have been found in simpler weakly nonlinear model equations such as the Kuramoto-Sivashinsky equation - see for example Akrivis *et al.* (2011). To accurately predict such dynamics we make use of the energy of the solution defined as

$$E(t) = \int_{-\pi/k}^{\pi/k} h^2(x, t) dx, \quad (3.1)$$

and note that this is computed with spectral accuracy either using Parseval's theorem since the Fourier coefficients are known, or using trapezoidal quadrature which is spectrally accurate for periodic functions; we also calculate dE/dt in order to construct phase planes presented below. Panels 4(a)-(b) give the evolution of $E(t)$ for $\tilde{Q} = 10$ and 100, respectively. In both cases we observe time periodic behaviour (approximately five periods of oscillation are included in each case) with the period decreasing as $\tilde{Q}$ increases. In fact the period for $\tilde{Q} = 10$ is approximately equal to 0.8 time units while that for $\tilde{Q} = 100$ it is approximately 0.08 time units, a decrease by a factor of 10 indicating that the frequency of oscillation is proportional to $\tilde{Q}$ when this becomes large - an asymptotic theory along with comparisons with the numerical data is presented in Section 6.1 for the more complicated case of wavy lower boundaries. Another feature of the results in figures 4(a)-(b) is the small amplitude of the time dependent oscillations about a mean value, with these amplitudes again decreasing as $\tilde{Q}$ increases. Confirmation of the time

FIGURE 4. Time evolution of the energy $E(t)$ for (a) $\tilde{Q} = 10$ and (b) $\tilde{Q} = 100$. Phase planes of the energy: E versus dE/dt for (c) $\tilde{Q} = 10$ and (d) $\tilde{Q} = 100$. All other parameters are the same as in figure 3.

periodicity of the solution is provided in the phase plane plots in panels 4(c)-(d) that have been produced for longer time intervals than those shown in panels (a) and (b). The two distinct loops correspond to the small and large amplitude superimposed oscillations of the two time signals.

We conclude that the dynamics in channels with flat walls lead to the formation of periodic “pillars” similar to the ones found experimentally by Schaffer *et al.* (2001) and theoretically by Craster & Matar (2005) in the absence of a background flow. However due to the presence of flow these structures travel down the channel and also undergo time-periodic modulations while keeping a finite separation distance from the walls.

4. Wavy lower boundary: interfacial response to non-uniform confinement geometries

In this section we present results of computations of (2.30) for a sinusoidal lower boundary given by

$$y = -z(x) = -Z_c + d_b \cos(k_b x). \quad (4.1)$$

The initial condition is (2.31) as before - recall that $2\pi/k$ selects the length of the computational domain. The parameter d_b measures the wall amplitude and k_b its wavenumber. When $d_b = 0$ we reduce to the flat case and we will use the linear stability results of Section 2.4 to guide the computations when $d_b \neq 0$. In particular for a given set of parameters the linear theory predicts a critical wavenumber k_c below which instability is supported and we investigate the two cases (a) $k < k_c$ and (b) $k > k_c$ to show that

FIGURE 5. Flow past a sinusoidal wavy wall of mean position $y = -0.9$ and having amplitude $d_b = 0.1$ and wavenumber $k_b = 4$ and $k_c = 1.87$; the scaled relative permittivities are $\bar{\epsilon}_1 = 1$ and $\bar{\epsilon}_2 = 5$, the flow rate is $\tilde{Q} = 0.1$ and the lower wall potential $V_b = 3$. (a) Initial condition (2.31) with $k = 2$. Interface $h(x, t)$ shown at time $t = 100$ after the solution has reached steady state. (b) Longer initial perturbation having $k = 1$. Interface $h(x, t)$ at $t = 1$ (dotted line), $t = 25$ (dot dashed line), $t = 75$ (dashed line) and $t = 100$ (solid line). The shaded area represents the lower boundary. A movie of the simulation for case (b) can be found in the supplementary file Movie1.avi.

they delineate distinct types of large time solutions. In case (b) the interface very quickly reaches a steady state and adopts the wavenumber k_b of the wavy boundary but with a much smaller amplitude; in case (a) we find travelling time-periodic structures that are similar to those for the flat boundary case seen in figure 3, but are modulated due to the wavy confining wall and “squeeze” past it. Typical results are given in figure 5 for wall parameters $k_b = 4$ and $d_b = 0.1$ and mean position $y = -Z_c = -0.9$; the other parameters are $\tilde{Q} = 0.1$ and $V_b = 3$. The results in panel 5(a) correspond to an initial condition having $k = 2$, i.e. it is twice the wavelength of the wavy wall. Note that this is larger than k_c for the chosen parameters and so the flow reaches a steady state (h is shown at $t = 100$ here) with the interface inheriting the pattern of the wavy wall but with a smaller amplitude of roughly 1.5×10^{-3} compared with $d_b = 0.1$. In panel 5(b) we set $k = 1 < k_c$ and observe that the unstable longer wavelength perturbation grows nonlinearly to travelling pillar like structures found for flat walls, but at the same time sweeps over the topography modulating its shape as it moves downstream. Profiles are shown at times ranging from $t = 1$ (dotted curve) to $t = 100$ (solid curve) and as found previously for flat walls, throughout the evolution the interface gets close to the upper and lower walls but does not touch them.

The results presented in figure 5 can be understood with a more detailed comparison with linear theory for flat walls. We can anticipate that as long as the wall amplitude d_b is not large - in the results $d_b = 0.1$ - the bifurcation from a non-uniform steady state to a more complicated modulated travelling wave, should correlate with flat wall linear theory. This is confirmed in the results presented in figure 6. We fix $k = 1$ in the initial conditions and compute solutions for a wavy wall having $d_b = 0.1$ and $k_b = 1$ at increasing values of V_b starting from $V_b = 1.5$. We quantify the solutions by estimating a wave speed c that measures the streamwise motion of the interfacial wave - the solution is not exactly a travelling wave of permanent form - it is time periodic and travelling. This is done by following trajectories in the $x - t$ plane of given points on the interface and defining a speed by estimating the slope of given trajectories using least squares regression. The results are given in figure 6(a) and it is seen that a bifurcation from stationary non-uniform steady state waves to travelling modulated waves, takes place

FIGURE 6. (a) Estimated interfacial wave speeds c for flows over a sinusoidal boundary with $d_b = 0.1$, $k_b = 1$ and $Z_c = 0.9$; (b) Neutral stability curve showing the critical wavenumber k_c as a function of V_b from linear theory with a flat bottom wall. The star corresponds to wavenumber $k_c = 1$ and $V_{crit} = 1.75$. The relative permittivities are $\bar{\epsilon}_1 = 1$ and $\bar{\epsilon}_2 = 5$ and the flow rate is $\tilde{Q} = 0.1$.

at a critical value $V_b \approx 1.75$. A direct comparison with the flat case linear theory is possible from the critical stability curve in $k_c - V_b$ space depicted in figure 6(b); in fact we find that k_c varies linearly with V_b and at $k_c = 1$ the critical value V_{crit} above which instability occurs is given by $V_{crit} = 1.75$, in complete agreement for the bifurcation value from steady to time modulated travelling waves for wavy walls. We conclude that there is a direct correlation between the stability of the flat and wavy wall cases; the critical voltage V_{crit} found for the flat case corresponds to the value V_b that marks the transition from steady state solutions to time modulated travelling waves.

4.1. Non-uniform steady states for different wall amplitudes

The transition between the two different types of solutions for the wavy boundary problem was described above and quantified using linear theory for flat walls. We now focus on calculating steady states of the evolution equation (2.30) by solving

$$\left\{ \frac{D_3}{6m_2} \left[D_4 p_{2x}^{(0)} + 3m_2 f_2 \right] \right\}_x = 0 \quad (4.2)$$

Equation (4.2) is solved using centred finite differences to discretise derivatives and a Newton-Kantorovich method to solve the resulting set of nonlinear algebraic equations. As a check the solutions were compared with those given by the time dependent code at least for values of $V_b < V_{crit}$ where the solutions are stable - for completeness this is included in figure 7(a) for $d_b = 0.1$, $k_b = 4$, $\tilde{Q} = 0.1$ and $V_b = 3$ and it is seen that agreement is excellent.

4.2. Analytical solution for small wall waviness

The steady states presented in §4.1 were calculated numerically for arbitrary wall waviness and in what follows we proceed analytically and construct asymptotic solutions valid for small wall perturbations. We can do this by writing the lower wall as $z(x) = Z_c + \varepsilon Z(x)$ where $\varepsilon \ll 1$, and looking for an asymptotic solution of the form $h(x) = \varepsilon H_0(x) + O(\varepsilon^2)$. Substituting these into (4.2) gives, to leading order

$$AH_0 + BH_{0x} + CH_{0xx} = -DZ - EZ_x, \quad (4.3)$$

FIGURE 7. (a) Comparison between the full time dependent numerical solution (solid line), the numerical solution of the steady state ODE (crosses) and the analytical solution (dots with equation (4.4)) with wall amplitude $\varepsilon = 0.1$. (b) Comparison between the analytical solution (solid curve with equation (4.4)) and the numerical solutions $h(x)/\varepsilon$ for $\varepsilon = 0.1$ (dashed line), $\varepsilon = 0.2$ (dot-dashed line) and $\varepsilon = 0.3$ (dotted line). Same parameters as in figure 5(a).

where A , B , C , D and E are constants that depend on the physical parameters in the problem (they are found as needed by using the symbolic manipulator Maple). To fix things we proceed with a sinusoidal wall perturbation of wavelength $2\pi/k_b$ and specifically take $Z(x) = -\cos(k_b x)$ in order to enable comparisons with nonlinear steady states computed for wavy wall perturbations given by (4.1). It follows that the general solution of equation (4.3) is given by

$$H_0(x) = \sum_{i=1}^3 C_i e^{\lambda_i x} + C_4 + \operatorname{Re}(p) \cos(k k_b x) - \operatorname{Im}(p) \sin(k k_b x), \quad (4.4)$$

where C_i , $i = 1, 2, 3, 4$ are constants and λ_i , $i = 1, 2, 3$ are the roots of $A + B\lambda + C\lambda^3 = 0$. The complex number p is given by

$$p = \frac{D + i k k_b E}{A + i k k_b B - i (k k_b)^3 C}.$$

The constants C_i , $i = 1, 2, 3, 4$ corresponding to the homogeneous solution, are found by imposing periodic boundary conditions over $x \in [-\pi/k, \pi/k]$ and the conservation of mass integral constraint on H_0

$$\int_{-\pi/k}^{\pi/k} H_0(x) dx = 0. \quad (4.5)$$

In the special case when k_b, k are integers with $k_b \neq \lambda_i$ for $i = 1, 2, 3$, it can be shown that the roots of $A + B\lambda + C\lambda^3 = 0$ are such that $\operatorname{Re}(\lambda) \neq 0$ and hence the homogeneous contribution to the solution cannot be spatially periodic. In such cases the expression for the interface simplifies to

$$H_0(x) = \operatorname{Re}(p) \cos(k k_b x) - \operatorname{Im}(p) \sin(k k_b x), \quad (4.6)$$

which can be interpreted as a phase shift in the interface position relative to the wall. In figure 7(a) we superimpose the leading order analytical solution (4.6) with $\varepsilon = 0.1$ along with the full time dependent numerical solution integrated to steady state, and the numerical solution of (4.2). Panel 7(b) considers larger wall amplitudes $\varepsilon = 0.2, 0.3$ and it can be seen that the leading order solution (4.6) is reasonably accurate even beyond its expected range of validity. Note that inclusion of ε^2 corrections is expected to improve the

FIGURE 8. Interface $h(x, t)$ at final times (a) $t=50$, (b) $t=100$, (c) $t=152$ and (d) $t=200$. Other arameters are $V_b = 7$, $\tilde{Q} = 0.0345$, $d_b = 0.4$, $k_b = 4$, $Z_c = 0.6$, $\beta = 1$, $\bar{\epsilon}_1 = 1$, $\bar{\epsilon}_2 = 2$, and $m_2 = 1$.

FIGURE 9. (a) Time evolution of the energy $E(t)$ of the solution presented in figure 8. (b) Phase plane of the energy: E versus dE/dt for times between $t = 200$ and $t = 600$.

agreement as found in the related studies of falling films over topography, e.g. Tseluiko *et al.* (2008).

4.3. Large amplitude sinusoidal boundary

In this section we examine the flow through highly constricted channels with wavy boundaries that occupy nearly half of the channel width. In the computations described next, the initial condition is chosen to be $h(x, 0) = 0$. For weak fields or in the absence of a field altogether, we would expect to reach the non-uniform steady states given by solutions

of (4.2). For large wall amplitudes, an additional physical feature of the steady states is the formation of vortices in the troughs that are now deep enough to accommodate them - see below for numerical results; for related single phase problems such as falling films over sinusoidally corrugated walls see the experiments of Pollak & Aksel (2013). At large enough values of the voltage parameter V_b , the unsteady numerical simulations predict that the interface initially reaches a state state, but eventually instability sets in with the dynamics transitioning to what we have termed “walking behaviour”. This behaviour can be mainly characterised by three stages: first the flow loses stability and parts of the interface get attracted to the lower wavy wall and other parts to the flat upper wall; this transient stage continues with the interface going into the troughs and over the crests in very close proximity to the wavy wall, with regions ahead (or behind) reaching the upper wall; finally the dynamics enters a final state that resembles a travelling wave, parts of which hug the lower wavy wall and other parts the upper wall. It is quite striking to discover that the resulting nonlinear dynamics are time periodic for a large range of parameters that were studied. Representative computations are provided in figure 8 for $V_b = 7$, $\tilde{Q} = 0.0345$, and a wavy wall with mean position $y = -0.6$, wall amplitude $d_b = 0.4$ and wavenumber $k_b = 4$. The scaled channel height is $y = 1$ ($\beta = 1$) and the scaled relative permittivities are $\bar{\epsilon}_1 = 1$, $\bar{\epsilon}_2 = 2$ (recall that $m_2 = 1$). Panel 8(a) shows the solution close to its unstable steady state at $t = 50$, while panels 8(b)-(d) at times $t = 100, 152, 200$ depict solutions from the three stages described above. For $t > 200$ the dynamics enters the time-periodic attractor mentioned earlier and this is quantified further in figure 9 that considers the flow from $t = 200$ to $t = 600$. Panel 9(a) shows the evolution of the energy norm $E(t)$ from $t = 0$ until the final time $t = 600$. It is seen that the solution quickly reaches a nonuniform steady state characterised by the the constant value $E(t) \approx 0.2$ until approximately $t = 70$, and then rapidly loses stability to a much higher energy state that eventually becomes time-periodic. Conclusive evidence of the time-periodicity is provided in panel 9(b) that constructs the energy phase plane which is seen to be a closed curve consisting of four almost congruent loops - inspection of panels (a) and (b) shows that there are four energy minima and four maxima over one period and the period is approximately equal to 130 time units.

In order to inspect the flow more thoroughly and in particular to obtain insight regarding the vorticity and subsequent mixing capabilities in such systems, we write the fluid velocity in the lower layer (analogously in the upper layer) in terms of the streamfunction $\psi(x, y)$ such that $u_2^{(0)} = \psi_y$ and $v_2^{(0)} = -\psi_x$. We note, however, that we are working within the lubrication approximation and it is likely that this assumption needs to be relaxed in order to obtain accurate re-circulation zones and subsequent mixing statistics. Using the expression for the horizontal fluid velocity given by equation (2.27) readily yields

$$\psi(x, y, t) = \frac{p_{2x}^{(0)}}{2m_2} \left(\frac{y^3}{3} - z(x)^2 y \right) + f_2 \left(\frac{y^2}{2} + z(x) y \right) + c_1(x), \quad (4.7)$$

where $c_1(x)$ is found by setting $\psi(x, -z(x), t) = 0$, i.e. the lower wall is defined to be a zero streamline. Figure 10 provides the instantaneous streamlines of the flow depicted in figure 8, at four consecutive times $t = 96, 98, 100, 106$ (the bar on the right shows the value of ψ in the contour plots). As described earlier and seen in figure 10, a distinct feature of the flow, at a fixed time, is that parts of the interface are in close proximity to troughs while ahead (behind) of these regions the interface climbs over the hump to reach the upper wall. What is interesting is that every time the interface goes over the wall humps and the lower fluid extends up to the upper wall, two strong counter

FIGURE 10. Instantaneous streamlines at (a) $t = 96$, (b) $t = 98$, (c) $t = 100$ and (d) $t = 106$. All other parameters as in figure 8.

rotating vortices form in close proximity to each other - see for example panel 10(d). As time increases these vortices get swept along downstream by the flow. A more detailed depiction of this flow feature is provided in figure 11 that shows an enlargement in the vicinity of the wall hump where the vortices are and at times before and after the hump. For example, the vortices at times $t = 126$ and $t = 146$ that are just over the hump, are seen to be more compact and the stream function attains much larger values compared with the other two times when the vortices are either behind or ahead of the hump. In turn, the vorticity generated is large and it may be possible to exploit such phenomena to induce electrostatically induced mixing at low Reynolds numbers and small flow rates.

We conclude this section by considering the same large amplitude wavy boundary as above but now take a smaller value $V_b = 2$. In such cases the interface reaches a steady state with vortices and flow recirculation taking place in the troughs, with the remaining flow unidirectionally moving over the peaks. Numerical results are given in figure 12 with panel (a) showing the interface at $t = 100$ after steady state has been reached, and panel (b) shows the streamlines of the corresponding state. The vortices are seen in the troughs and we note that they are fairly weak with the flow in their vicinity almost stagnant.

The results in this section indicate that for a given imposed flow rate the wall geometry and electric field can be manipulated to obtain dynamical behaviour in confined micro scale geometries that may be useful in applications. The structures computed are fully nonlinear and are most likely not amenable to analytical descriptions. They are underpinned by loss of stability of nonuniform steady states and in what follows we consider such stability questions analytically using linear Floquet analysis.

FIGURE 11. Instantaneous streamlines at (a) $t = 106$, (b) $t = 126$, (c) $t = 146$ and (d) $t = 157$. All other parameters as in figure 8.

FIGURE 12. (a) Interface $h(x, t)$ and (b) streamlines at time $t=100$. Parameters are the same as in figure 8 but with a different voltage $V_b = 2$.

5. Floquet stability analysis of nonuniform flows

The objective of this section is to use linear stability theory to establish ranges of values of V_b for which the flow transitions from nonuniform steady states to the “walking behaviour” we described in the previous section. A natural setting for the analysis is to use Floquet theory since the underlying flows are spatially periodic. Given a steady state $h_s(x)$ that solves equation (4.2), we write $h(x, t) = h_s(x) + \tilde{h}(x, t)$, substitute into (2.30) and linearise to obtain

$$\tilde{h}_t + \left[f_1 \tilde{h} + f_2 \tilde{h}_x + f_3 \tilde{h}_{xxx} \right]_x = 0, \quad (5.1)$$

FIGURE 13. (a) Real part of the growth rate λ as the applied voltage V_b is varied for a flat boundary case. (b) Real part of the growth rate s versus wavenumber k as calculated from the linear stability analysis in §2.4 for $V_b = 3$ (solid line), $V_b = 6$ (dashed line), $V_b = 8.9$ (dot-dashed line) and $V_b = 11.8$ (dotted line). Other parameters are $\tilde{Q} = 0.1$, $\beta = 1$, $\bar{\epsilon}_1 = 1$, $\bar{\epsilon}_2 = 2$, $m_2 = 1$.

where $f_i = f_i(h_s, h_{sx}, h_{sxxx}, z, z_x)$ for $i = 1, 2, 3$ are periodic functions of x with the same period as the steady state solution, and they are found using Maple. Looking for solutions of the form

$$\tilde{h}(x, t) = F(x) \exp(\lambda t + ikx),$$

where $F(x)$ is a periodic function with the same spatial period as $\tilde{h}(x, t)$ and the eigenvalue λ is complex, equation (5.1) becomes

$$\begin{aligned} \lambda F + F [f_{1x} + ik(f_1 + f_{2x} - k^2 f_2 - ik^3 f_{3x} + k^4 f_3)] + \\ + F' [f_1 + f_{2x} + 2ikf_2 - 3k^2 f_{3x} - 4ik^4 f_3] + \\ + F'' [f_2 + 3ikf_{3x} - 6k^2 f_3] + F''' [f_{3x} + 4ikf_3] + F'''' [f_3] = 0. \end{aligned} \quad (5.2)$$

In the calculations that follow we consider perturbations of the same wavelength as the underlying solution, and so set $k = 0$ in equation (5.2). This simplification provides a sufficient condition for instability, and is justified since we expect the flow to be long wave unstable as is the case when the lower wall is flat. In what follows we analyse a typical case having flow rate $\tilde{Q} = 0.1$, and sinusoidal lower wall topography of amplitude $d_b = 0.4$, wavenumber $k_b = 4$ and mean value $y = -Z_c = -0.6$; other parameters are as before with $\beta = 1$, $\bar{\epsilon}_1 = 1$, $\bar{\epsilon}_2 = 2$, $m_2 = 1$. Keeping these parameters fixed, we vary the voltage V_b and compute the eigenvalues λ numerically. For each V_b we find n eigenvalues where n is the number of discretisation points in x . Derivatives of $F(x)$ are found using spectral differentiation matrices. Since we are essentially interested in detecting instability as V_b varies, we found it useful to track only those eigenvalues whose real part is sufficiently large, and used $\text{Re}(\lambda) > -0.4$.

The code was tested for the trivial case of a flat wall and hence $h_s(x) = 0$, against the results given in §2.4. In the Floquet setting of this problem we need to solve

$$\lambda F + AF_x + BF_{xx} + CF_{xxx} = 0 \quad (5.3)$$

where A , B and C are the same constants as the ones found in equation (4.3). The calculated real part of λ versus V_b is given in figure 13(a) where as noted above, only eigenvalues greater than -0.4 are shown. The results show different modes and how they become unstable as V_b increases. The first mode becomes unstable when $V_b = 3$, and then there are subsequent crossings by the second mode at $V_b = 6$, the third at $V_b = 8.9$ and the fourth at $V_b = 11.8$. Panel 13(b) shows the growth rate as a function of wavenumber for different V_b as found in §2.4. The values of V_b above which the modes $k = 1, 2, 3, 4$

FIGURE 14. (a) Real part of the growth rate λ versus applied voltage V_b . Same parameters as in figure 13 with $d_b = 0.4$, $k_b = 4$ and $Z_c = 0.6$. (b) Time evolution of the energy $E(t)$. Applied voltage is $V_b = 5.4$ (dot-dashed line) and $V_b = 5.6$ (solid line). The bottom figures show the phase plane of the energy for (c) $V_b = 5.4$ and (d) $V_b = 5.6$. Simulations of interfacial evolution for $V_b = 5.4$ and $V_b = 5.6$ can be found in Movie2.avi and Movie3.avi respectively.

FIGURE 15. (a) Interface $h(x, t)$ at $t_{final} = 300$ for same parameters as figure 14 and $V_b = 20$. (b) Minimum of the gap between the interface and the boundary against time.

become successively unstable, are confirmed to be the same as those found using the Floquet analysis.

Next we consider the case with a wavy boundary and parameters as given above, and compute the eigenvalues λ from equation (5.2) with $k = 0$. Figure 14(a) shows the variation of the real part of λ with V_b , and note that the first crossing yielding instability occurs at $V_b = 2.6$. This has been confirmed from the nonlinear time dependent computations that predict stability of nonuniform states for these parameters when $V_b <$

2.6. The next mode crossing to become unstable occurs at around $V_b = 5.2$. Some intricate behaviour is found near this point and the inset in figure 14(a) depicts branches in more detail. It is seen that the branch that crossed at $V_b \approx 5.2$ itself pitchfork bifurcates at $V_b \approx 5.5$ into two branches. To observe the differences in the dynamics, we took values $V_b = 5.4$ and $V_b = 5.6$ that are below and above the critical value $V_b = 5.5$, and ran large time simulations of the nonlinear initial value problem. We find that the solution transitions into the “walking behaviour” described earlier and the energy norms along with the corresponding phase planes are included in panels 14(b)-(d). The lower voltage energy norm is less intricate than that for $V_b = 5.6$ in the sense that it does not contain as high frequency oscillations. It is also clear from figure 14(b) that the time-averaged energy values are different and we can conclude that the two solutions are on different branches. More information regarding the dynamics of these solutions are given in the phase planes in panels 14(c)-(d) - even though we cannot state this conclusively, it appears that the dynamics for $V_b = 5.4$ are quasi-periodic in time whereas those for $V_b = 5.6$ are periodic and more analogous to those found earlier - e.g. figure 9.

The results presented in figure 14 are for moderate values of $V_b \leq 8$. Even though a detailed bifurcation study and stability of the resulting branches is of intrinsic interest, it is beyond the aims of this work, but we illustrate the richness of expected behaviour by considering several larger values of V_b . For example, solution of the initial value problem starting from a flat interface (all other parameters as in figure 14) and for a relatively high voltage of $V_b = 20$, indicates that after some initial transient oscillations appears to reach a steady state that is stuck at the lower wall troughs but is well separated from the upper wall. Figure 15 shows the solution at a final computed time $t_{final} = 300$ and closer inspection of the results shows that the thin films of the lower fluid that form on the wall humps are slowly draining with time. The minimum thickness of these films is plotted against time in panel 15(b) and the slow draining is clearly observed. This solution is another attracting state, albeit quasi-static, and essentially asymptotically traps regions of fluid 2 between successive wall humps with the upper fluid 2 flowing above them as can be seen from figure 15(a). We note that the simulations indicate that the film thickness does not vanish in finite time in agreement with other related thinning film problems - see for example Craster & Matar (2005), Tseluiko & Papageorgiou (2007b). (Physically, addition of attracting van der Waals forces would rupture the thin film in finite time, see Erneux & Davis (1993), Savettaseranee *et al.* (2003).) For $V_b = 8.5$ we see the two attracting states competing with each other with the solution going to the “stuck” behaviour first and then going into a “walking” behaviour. In the former state, the solution undergoes time periodic oscillations without translating down the channel, before losing stability to the “walking” state. Snapshots of the two solutions are included in figure 17(a) at times $t = 60$ (dashed curve) and $t = 300$ (solid curve), along with the evolution of the energy $E(t)$ that indicates the time periodic behaviour at smaller times and the transition to the “walking” state at larger times. Note that the “walking” state evolves time periodically with a much longer period than that of the “stuck” solution. A movie of the interfacial evolution is also included - see caption of figure 17.

6. Flows at high fluxes $\tilde{Q}$

So far we have explored the behaviour of the system for a low overall flow rates characterised by small values of $\tilde{Q}$. In this section we consider the behaviour of the confined electrified flow over large amplitude sinusoidal topography and at relatively large values of $\tilde{Q}$. To fix matters we consider the same parameters as before (e.g. figure 14) but now take $\tilde{Q} = 20$ and vary the voltage parameter V_b .

FIGURE 16. Real part of the growth rate λ versus the applied voltage V_b . Same parameters as figure 14 but with $\tilde{Q} = 20$.

FIGURE 17. (a) Interface at times $t = 60$ (dashed curve) and $t = 300$ (solid curve) for same parameters as figure 14 and $V_b = 8.5$. (b) Energy $E(t)$ plotted as time is varied. A simulation of the interfacial evolution is given in Movie4.avi.

FIGURE 18. (a) Interface $h(x, t)$ at $t = 1$ (dotted line), $t = 25$ (dot-dashed line), $t = 75$ (dashed line) and $t = 100$ (solid line). (b) Streamlines at time $t = 100$. Parameters are the same as in figure 8 but with $V_b = 14$ and $\tilde{Q} = 20$.

We begin by considering the linear stability of the nonuniform steady states for $\tilde{Q}$ as V_b varies. The results are shown in figure 16 that depicts the real part of λ for different V_b . It is found that there is a crossing at $V_b \approx 9.1$ so that all perturbations with wavelength equal to the domain size are stable for voltages below this value. Comparing these results

FIGURE 19. *a*) Full numerical solution minus the steady state solution $h(x, t) - h_0(x)$ (dashed line) compared with the asymptotic solution $\delta H(x, \tau)$ (solid line) at four different times with $t = \tau/\tilde{Q}$. *b*) Phase plane of the energy $E(t)$. *c*) $E(t)$ plotted as time t is varied. *d*) $E(\tau)$ plotted as time τ is varied.

with those in figure 14 that has $\tilde{Q} = 0.1$, we can conclude that generally a higher flow rate has a stabilising effect.

To investigate the dynamics into the unstable regime we pick $V_b = 14$ which according to the results in figure 16 supports three unstable modes. The initial value problem is solved starting from a flat interface initial condition and following the nonlinear development until $t = 100$ or more. Representative results are given in figure 18; panel 18(a) shows the interfacial shape at $t = 1, 25, 75$ and 100 and the results predict clearly that at this moderately large value of $\tilde{Q} = 20$ the interface mimics the lower wall topography but at the same time performs small amplitude high frequency time-dependent oscillations. Panel 18(b) shows the instantaneous streamlines at the final time $t = 100$ and we can see that the fluid flows over the topography without any vortices present - we note that such regimes are therefore not advantageous for mixing or fluid trapping phenomena found earlier.

6.1. Asymptotic Solution for large $\tilde{Q}$

The results in figure 18 (as well as several other numerical experiments not reported here) suggest that as $\tilde{Q}$ increases the flow is a steady state that is modulated spatiotemporally by a small amplitude and high frequency component. This observation is now formalised by considering asymptotic solutions to equation (2.30) for large $\tilde{Q}$. Setting $\delta = 1/\tilde{Q} \ll 1$, we seek a solution of (2.30) of the form

$$h(x, t) = h_0(x) + \delta H(x, \tau) + \dots, \quad \tau = t/\delta, \quad (6.1)$$

where $h_0(x)$ is the steady state solution at these parameter values, i.e. a solution of (4.2). The equation for $H(x, \tau)$ emerges at $\mathcal{O}(\delta)$ and reads

$$H_\tau + \left\{ \tilde{F}(h_0(x), z(x)) H \right\}_x = 0, \quad (6.2)$$

where $\tilde{F}$ is a function of $h_0(x)$, the lower boundary shape $z(x)$ and its only other dependence is on the physical parameters of the system.

Equation (6.2) is solved numerically for an initial condition given by the full time dependant numerical solution at a selected time (and after transients have died out) minus the steady state $h_0(x)$, and with $\tilde{Q} = 100$ (so that $\delta = 0.01$). The asymptotic solution $\delta H(x, t/\delta)$ is compared with $h(x, t) - h_0(x)$ in figure 19(a) for four different times and we see that the agreement between the two is excellent. Panel 19(b) shows the phase plane of the energy of $h(x, t) - h_0(x)$ coming from the full numerical computation - the spatiotemporal modulation mentioned above is clearly seen from the figure. Panel 19(c) shows the evolution of $E(t)$ over approximately ten oscillation cycles. In panel 19(d) we include the evolution in τ of the energy $E_a(\tau) = \int_{-\pi}^{\pi} \delta^2 H^2(x, \tau) dx$ of the asymptotic correction, where once again ten oscillation cycles are included. This data was used to estimate the frequencies f_t and f_τ of oscillation of the full and asymptotic solutions, respectively. We find that $f_t/f_\tau \approx 100 = \tilde{Q} = 1/\delta$ as expected. This provides additional evidence of the relevance of the asymptotic solutions at large $\tilde{Q}$. Good agreement was found for $\tilde{Q}$ as small as 10.

7. Conclusions

We have examined the stability and nonlinear dynamics of electrified pressure-driven stratified two-fluid flows in channels with non-uniform cross sections. This was achieved by using a long-wavelength approximation to derive a spatially one-dimensional evolution equation for the sharp interface between the two fluids. In this asymptotic limit, knowledge of the interfacial position recovers the flow field anywhere in the channel, and the dynamics were probed by constructing and studying streamline and vorticity plots. The system is parametrized by several physically crucial parameters including the dimensionless flow rate, the strength of the dimensionless electric field applied across the channel, and the ratios of viscosities and permittivities between the two phases. The present study considered the case of equal fluid viscosities in order to reduce the number of parameters; such a choice is not physically restrictive since in this inertialess limit there are no viscosity stratification instabilities - see Yih (1967).

The case of a uniform thickness channel with a flat lower boundary was explored first. Linear stability analysis showed that in the presence of a vertical electric field the system is unstable over a finite range of wave numbers. To confirm this prediction and to follow the dynamics into the nonlinear regime, the evolution equation was solved numerically using a spectral method in space and an implicit time marching scheme in time. The results predict that small initial perturbations evolve to take the form of columnar travelling wave structures that are reminiscent of those found by Craster & Matar (2005) in the absence of a driving pressure gradient. A crucial finding of our computations is that the presence of flow prevents the interface from touching the upper or lower wall and in fact the minimum film thickness increases with the flux $\tilde{Q}$ - see figure 3(b). In addition, the emerging large amplitude coherent structures are not exact travelling waves but are modulated time-periodically by small perturbations that decrease as $\tilde{Q}$ increases - the interfacial waves appear to generically develop into time-periodic travelling waves.

Next, a relatively small waviness (of crest to trough amplitude that is $1/10$ the channel thickness) was imposed on the lower boundary and two types of behaviour were broadly observed. For interfacial perturbations with wavenumbers that are unstable in the case of flat boundaries, time-periodic travelling wave structures develop as before but have their shape additionally affected by the topography by sweeping over the undulations cushioned by thin topography following films (see supplementary file *Movie1.avi* for example). The topography typically has a shorter period than that imposed on the interface, so that structures that are subharmonic with respect to the topography can emerge. For interfacial perturbations that are sufficiently short to be stable in the uniform thickness channel case, the interface reaches a steady state that adopts the periodicity of the lower boundary. By tracking the effective speed of the waves in the wavy boundary case, it is shown that the transition from nonuniform steady states to time-periodic travelling waves occurs at a critical voltage that can be found from the linear stability for the flat boundary case. When the voltage is below this critical value and steady states emerge, we also presented an analytical solution valid for small wall corrugation amplitudes. These asymptotic solutions were compared with full numerical ones and good agreement was found for dimensionless wall amplitudes as large as 0.2 or 0.3 for dimensionless channels of thickness 2 units.

The amplitude of the boundary was increased (to typical crest to trough values of 0.8), and the problem was solved numerically starting from initial conditions with the interface flat. The interaction of the two fluids with the wavy boundary is found to be more pronounced than before - it is also established that the linear theory for flat walls is no longer informative or predictive as for small amplitude corrugations. Computations over relatively long domains that include four periods of wall oscillations, we find that below a critical applied voltage the flow reaches a steady state that is synchronous with the wall undulations. For the particular case of wall amplitude $d_b = 0.4$ and relatively small flow rates such steady states are typically characterized by interfacial amplitudes that are an order of magnitude smaller than those of the boundary (see figure 12(a) for the case $V_b = 2$), but which produce a flow with trapped vortices in the troughs of the wavy wall as shown in figure 12(b), for example (such recirculation zones may be favourable for applications such as cell trapping). As the voltage is increased further, the steady state loses stability and a large amplitude interfacial wave forms and starts sliding over the boundary (no wall touchdown was found in any of the cases computed with non-zero flow rate). Once this regime sets in, then for a range of voltages the interface exhibits a “walking” motion which causes the fluid in the lower layer to alternate between sliding through the troughs and forming strong vortices above the wall crests - see figures 8, 10, 11 (this regime may be useful for microfluidic mixing applications as well as enhancing fluid transport). The stability of the nonuniform steady states was analyzed by using a Floquet analysis that proved successful in identifying the ranges of voltages supporting each type of behaviour. To complete the analysis, we also considered large overall flow rate and found that its effect is to stabilise the system and in particular suppress vortical structures in the vicinity of the topographically structured substrate. Numerical simulations indicate that for high flow rates the topography interacts much more strongly with the interface even when the wavy boundary has small amplitudes. Finally, an asymptotic solution was developed for large values of the overall flow rate $\hat{Q}$ and compared with the numerical computations showing excellent agreement. The solution features in this limit are a non-uniform steady state to leading order that is modulated by small time dependent high frequency modulations.

The system has a rich variety of behaviours and we have chosen to analyse and present a few of the most interesting cases. The present article aims to give insight on the

influence of a patterned electrode on the interface between two perfect dielectric fluids. Future work will consider in phase and out of phase topographical structuring of both channel walls and the subsequent effects of an applied voltage to such systems. Such geometries may be of particular relevance to microfluidic channels used in practice - see Song *et al.* (2006)

Acknowledgements

ED acknowledges support from NERC for a PhD scholarship. The work of RVC and DTP was supported by the EPSRC under grants EP/L020564/1 and EP/K041134/1. Alice Thompson is also thanked for many useful discussions.

Appendix A. Functions from section §2.3

In this Appendix we provide the details of the constants and of the functions of $h(x, t)$ that feed into the evolution eq.(2.30):

$$h_t + \left\{ \frac{D_3}{6m_2} \left[D_4 p_{2x}^{(0)} + 3m_2 f_2 \right] \right\}_x = 0 \quad (\text{A } 1)$$

where

$$D_1 = -(h - \beta)^2, \quad D_2 = h + 2\beta, \quad D_3 = (h + z)^2, \quad D_4 = h - 2z. \quad (\text{A } 2)$$

$$d_1 = \frac{\epsilon_2 V_b}{\epsilon_2(h - \beta) - \epsilon_1(h + z)}, \quad d_2 = \frac{\epsilon_1 V_b}{\epsilon_2(h - \beta) - \epsilon_1(h + z)} \quad (\text{A } 3)$$

$$\begin{aligned} E_1 &= (h - \beta) - \frac{m_1}{m_2}(h + z), \\ E_2 &= - \left[\frac{h^2 - \beta^2}{2m_1} - \frac{h(h + z)}{m_2} \right], \\ E_3 &= - \frac{(h + z)^2}{2m_2}, \\ E_6 &= - \frac{D_1 D_2}{6m_1} - \frac{E_2 D_1}{E_1} - \frac{D_3}{2} [h + (E_2 m_1 / E_1)], \\ E_7 &= - \frac{D_1 E_3}{2E_1} + \frac{E_3 D_4}{3} - \frac{D_3}{2} [(E_3 m_1 / E_1) - h]. \end{aligned} \quad (\text{A } 4)$$

$$\begin{aligned} f_1(x, t) &= \frac{E_2 p_{1x}^{(0)} + E_3 p_{2x}^{(0)}}{E_1}, \\ f_2(x, t) &= \frac{1}{m_2} \left\{ \left[h + \frac{E_2}{E_1} m_1 \right] p_{1x}^{(0)} + \left[\frac{E_3}{E_1} m_1 - h \right] p_{2x}^{(0)} \right\}, \\ p_{1x}^{(0)} &= p_{2x}^{(0)} + h_{xxx} + \epsilon_1 d_{1x} d_1 - \epsilon_2 d_{2x} d_2, \\ p_{2x}^{(0)} &= \frac{-E_6(h_{xxx} + \epsilon_1 d_{1x} d_1 - \epsilon_2 d_{2x} d_2) - \tilde{Q}}{E_6 + E_7}. \end{aligned} \quad (\text{A } 5)$$

REFERENCES

- AKRIVIS, G., PAPAGEORGIOU, D. T. & SMYRLIS, Y.-S. 2011 Linearly implicit methods for a semi linear parabolic system arising in two-phase flows. *IMA Journal of Numerical Analysis* **31**, 299–321.
- ANDERSSON, H. & VAN DEN BERG, A. 2003 Microfluidic devices for cellomics: a review. *Sensors and actuators B: Chemical* **92** (3), 315–325.
- BARANNYK, L.L., PAPAGEORGIOU, D. T., PETROPOULOS, P.G. & VANDEN-BROECK, J.-M. 2015 Nonlinear dynamics and wall touch-up in unstably stratified multilayer flows in horizontal channels under the action of electric fields. *SIAM Journal on Applied Mathematics* **75**, 92–113.
- BIELARZ, C. & KALLIADASIS, S. 2003 Time-dependent free-surface thin film flows over topography. *Phys. Fluids* **15** (9), 2512–2524.
- CHOU, S. Y. & ZHUANG, L. 1999 Lithographically induced self-assembly of periodic polymer micropillar arrays. *Journal of Vacuum Science & Technology B* **17** (6), 3197–3202.
- CRASTER, R. V. & MATAR, O. K. 2005 Electrically induced pattern formation in thin leaky dielectric films. *Physics of Fluids (1994-present)* **17** (3), 032104.
- CRASTER, R. V. & MATAR, O. K. 2009 Dynamics and stability of thin liquid films. *Reviews of modern physics* **81** (3), 1131.
- DAVIS, M.J., GRATTON, M.B. & DAVIS, S.H. 2010 Suppressing van der waals driven rupture through shear. *J. Fluid Mech.* **661**, 522–539.
- ERICKSON, D. & LI, D. 2004 Integrated microfluidic devices. *Analytica Chimica Acta* **507** (1), 11–26.
- ERNEAUX, T. & DAVIS, S.H. 1993 Non linear rupture of free films. *Phys. Fluids A* **5**, 1117–1122.
- HEIER, J., GROENEWOLD, J. & STEINER, U. 2009 Pattern formation in thin polymer films by spatially modulated electric fields. *Soft Matter* **5**, 3997–4005.
- KALPATHY, S. K., FRANCIS, L. F. & KUMAR, S. 2010 Shear-induced suppression of rupture in two-layer thin liquid films. *J. Colloid Interface Sci.* **348**, 271–279.
- KARAPETSAS, G. & BONTZOGLIOU, V. 2015 Non-linear dynamics of a viscoelastic film subjected to a spatially periodic electric field. *Journal of Non-Newtonian Fluid Mechanics* **217**, 1–13.
- KHANDURINA, J. & GUTTMAN, A. 2002 Bioanalysis in microfluidic devices. *Journal of Chromatography A* **943** (2), 159–183.
- LENZ, R. D. & KUMAR, S. 2007 Steady two-layer flow in a topographically patterned channel. *Physics of Fluids (1994-present)* **19** (10), 102103.
- LI, F., OZEN, O., AUBRY, N., PAPAGEORGIOU, D. T. & PETROPOULOS, P. G. 2007 Linear stability of a two-fluid interface for electrohydrodynamic mixing in a channel. *Journal of Fluid Mechanics* **583**, 347–377.
- LUO, H. & POZRIKIDIS, C. 2006 Shear-driven and channel flow of a liquid film over a corrugated or indented wall. *Journal of Fluid Mechanics* **556**, 167–188.
- MAEHLMANN, S. & PAPAGEORGIOU, D. T. 2011 Interfacial instability in electrified plane couette flow. *Journal of Fluid Mechanics* **666**, 155–188.
- MELCHER, J. R. & TAYLOR, G. I. 1969 Electrohydrodynamics: A review of the role of interfacial shear stresses. *Annual Reviews of Fluid Mechanics* **1**, 111–146.
- NIE, Z. & KUMACHEVA, E. 2008 Patterning surfaces with functional polymers. *Nature Materials* **7** (4), 277–290.
- OZEN, O., AUBRY, N., PAPAGEORGIOU, D.T. & PETROPOULOS, P.G. 2006 Electrohydrodynamic linear stability of two immiscible fluids in channel flow. *Electrochimica Acta* **51**, 5316–5323.
- PAPAEFTHYMIU, E. S., PAPAGEORGIOU, D. T. & PAVLIOTIS, G. A. 2013 Nonlinear interfacial dynamics in stratified multilayer channel flows. *Journal of Fluid Mechanics* **734**, 114–143.
- PEASE, L. F. & RUSSELL, W. B. 2002 Linear stability analysis of thin leaky dielectric films subjected to electric fields. *Journal of Non-Newtonian Fluid Mechanics* **102** (2), 233–250.
- PETZOLD, L. R. 1982 A description of DASSL: A differential/algebraic system solver. *Proc. IMACS World Congress* pp. 430–432.
- POLLAK, T. & AKSEL, N. 2013 Crucial flow stabilisation and multiple instability branches of gravity-driven films over topography. *Phys. Fluids* **25**, 024103.

- RAMKRISHNAN, A. & KUMAR, S. 2014 Electrohydrodynamic deformation of thin liquid films near surfaces with topography. *Physics of Fluids (1994-present)* **26** (12), 122110.
- SAVETTASERANEE, K., PAPAGEORGIOU, D.T., PETROPOULOS, P.G. & TILLEY, B.S. 2003 The effect of electric fields on the rupture of thin viscous films by van der waals forces. *Phys. Fluids* **15**, 641–652.
- SAVILLE, D. A. 1997 Electrohydrodynamics: the Taylor-Melcher leaky dielectric model. *Annual review of fluid mechanics* **29** (1), 27–64.
- SCHAFER, E., THURN-ALBRECHT, T., RUSSELL, T. P. & STEINER, U. 2000 Electrically induced structure formation and pattern transfer. *Nature* **403** (6772), 874–877.
- SCHAFER, E., THURN-ALBRECHT, T., RUSSELL, T. P. & STEINER, U. 2001 Electrohydrodynamic instabilities in polymer films. *EPL (Europhysics Letters)* **53** (4), 518.
- SONG, HELEN, CHEN, DELAI L. & ISMAGILOV, RUSTEM F. 2006 Reactions in droplets in microfluidic channels. *Angewandte Chemie International Edition* **45** (44), 7336–7356.
- SOOHOO, J. R. & WALKER, G. M. 2009 Microfluidic aqueous two phase system for leukocyte concentration from whole blood. *Biomedical microdevices* **11** (2), 323–329.
- THAKAR, R.M. & KUMARAN, V. 2005 Electrohydrodynamic instability of the interface between two fluids confined in a channel. *Phys. Fluids* **17**, 084104.
- TONER, M. & IRIMIA, D. 2005 Blood-on-a-chip. *Annual review of biomedical engineering* **7**, 77.
- TSELUKO, D., BLYTH, M. G., PAPAGEORGIOU, D. T. & VANDEN-BROECK, J. M. 2008 Electrified viscous thin film flow over topography. *Journal of Fluid Mechanics* **597**, 449–475.
- TSELUKO, D. & PAPAGEORGIOU, D. T. 2006 Wave evolution on electrified falling films. *Journal of Fluid Mechanics* **556**, 361–386.
- TSELUKO, D. & PAPAGEORGIOU, D. T. 2007a Dynamics of a viscous thread surrounded by another viscous fluid in a cylindrical tube under the action of a radial electric field: breakup and touchdown singularities. *SIAM Journal on Applied Mathematics* **67**, 1310–1329.
- TSELUKO, D. & PAPAGEORGIOU, D. T. 2007b Nonlinear dynamics of electrified thin liquid films. *SIAM Journal on Applied Mathematics* **67**, 1310–1329.
- UGUZ, A.K. & AUBRY, N. 2008 Quantifying the linear stability of a flowing electrified two-fluid layer in a channel for fast electric times for normal and parallel electric fields. *Phys. Fluids* **20**, 092103.
- WU, N. & RUSSELL, W. B. 2009 Micro-and nano-patterns created via electrohydrodynamic instabilities. *Nano Today* **4** (2), 180–192.
- YI, C., LI, C. W., JI, S. & YANG, M. 2006 Microfluidics technology for manipulation and analysis of biological cells. *Analytica Chimica Acta* **560** (1), 1–23.
- YIH, C.-S. 1967 Instability due to viscosity stratification. *Journal of Fluid Mechanics* **27**, 337–352.
- ZHOU, C. & KUMAR, S. 2012 Two-dimensional two-layer channel flow near a step. *Chem. Eng. Sci.* **81**, 38–45.